3.0 A, 2.4 MHz, Digitally Programmable Buck Regulator

FAN53528

WLCSP−15
CASE 567QS

MARKING DIAGRAM

1, 2 = Two Alphanumeric Characters for Device Mark
KK = Two Alphanumeric Characters for Lot Rune Code Mark
. = Pin 1 Indicator
X = Alphabetical Year Code
Y = 2−weeks Date Code
Z = Assembly Plant Code

ORDERING INFORMATION

See detailed ordering and shipping information on page 2 of this data sheet.

DISCONTINUED
THIS DEVICE IS NOT RECOMMENDED FOR NEW DESIGN
PLEASE CONTACT YOUR onsemi
REPRESENTATIVE FOR INFORMATION

Descriptions

The FAN53528 is a step−down switching voltage regulator that delivers a digitally programmable output from an input voltage supply of 2.5 V to 5.5 V. The output voltage is programmed through an I^2C interface capable of operating up to 3.4 MHz.

Using a proprietary architecture with synchronous rectification, the FAN53528 is capable of delivering 3.0 A continuous at over 80% efficiency, maintaining that efficiency at load currents as low as 10 mA. The regulator operates at a nominal fixed frequency of 2.4 MHz, which reduces the value of the external components. Additional output capacitance can be added to improve regulation during load transients without affecting stability.

At moderate and light−loads, Pulse Frequency Modulation (PFM) is used to operate in Power−Save Mode with a typical quiescent current of 50 mA at room temperature. Even with such a low quiescent current, the part exhibits excellent transient response during large load swings. At higher loads, the system automatically switches to fixed−frequency control, operating at 2.4 MHz. In Shutdown Mode, the supply current drops below 1 mA, reducing power consumption. PFM Mode can be disabled if fixed frequency is desired. The FAN53528 is available in a 15−bump, 1.[illegible]0 mm × 2.015 mm, 0.4 mm ball pitch WLCSP.

Features

- Fixed−Frequency Operation: 2.4 MHz
- Best−in−Class Load Transient
- Continuous Output Current Capability: 3.0 A
- 2.5 V to 5.5 V Input Voltage Range
- Digitally Programmable Output Voltage:
  - 0.35 V to 1.14375 V in 6.25 mV Steps
- Programmable Slew Rate for Voltage Transitions
- I^2C−Compatible Interface Up to 3.4 Mbps
- PFM Mode for High Efficiency in Light−Load
- Quiescent Current in PFM Mode: 50 μA (Typical)
- Input Under−Voltage Lockout (UVLO)
- Thermal Shutdown and Overload Protection
- 15−Bump Wafer−Level Chip Scale Package (WLCSP)

Applications

- Application, Graphic, and DSP Processors
  - ARM™, Tegra™, OMAP™, NovaThor™, ARMADA™, Krait™, etc.
- Hard Disk Drives, LPDDR3, LPDDR4
- Tablets, Netbooks, Ultra−Mobile PCs
- Smart Phones

© Semiconductor Components Industries, LLC, 2016

- Gaming Devices

Figure 1. Typical Application

PACKAGE MARKING AND ORDERING INFORMATION

Part Number	Power−Up Defaults		EN Delay	Temperature Range	Package	Packing Method	Device Marking
	VSEL0	VSEL1					
FAN53528BUC08X	0.4	0.6	No	−40 to 85°C	WLCSP	Tape & Reel	FX
FAN53528DUC40X	0.6	0.9	No				FY
FAN53528GUC48X	0.65	0.7	No				FZ
FAN53528EUC48X	0.65	0.7	5 ms				FW
*FAN53528DUC1204X	1.1	0.9					TBD

†For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.
*This device is not released yet.

DISCONTINUED
THIS DEVICE IS NOT RECOMMENDED FOR NEW DESIGN
PLEASE CONTACT YOUR onsemi
REPRESENTATIVE FOR INFORMATION

RECOMMENDED EXTERNAL COMPONENTS

Table 1. RECOMMENDED EXTERNAL COMPONENTS FOR 3.0 A MAXIMUM LOAD CURRENT

Component	Description	Vendor	Parameter	Typ.	Unit
L1	330 nH, 2016 Case Size	See Table 2			
L1 Alternative (Note 1)	470 nH 2016 Case Size				
C_{OUT1}, C_{OUT2}	22 μF, 6.3 V, X5R, 0603	C1608X5R0J226M080AC (TDK)	C	22	μF
C_{IN}	1 Piece; 4.7 μF, 10 V, X5R, 0603	C1608X5R1A475K (TDK)	C	4.7	
C_{BY} (Note 1)	1 Piece; 100 nF, 6.3V, X5R, 0201	GRM033R60J104KE19D (Murata)	C	100	nF

1. L1 Alternative can be used if not following reference design. C_{BY} is recommended to reduce any high frequency component on VIN bus. C_{BY} is optional and used to filter any high frequency component on VIN bus.

Table 2. RECOMMENDED INDUCTORS

Manufacturer	Part #	L (nH)	DCR (mΩ Typ.)	I_{SAT} (Note 2)	Component Dimensions		
					L	W	H
Toko	DFE201610E−R33N	330	21	6.1	2.0	1.6	1.0
Toko	DFE201610E−R47N	470	26	5.3	2.0	1.6	1.0

2. I_{SAT} where the dc current drops the inductance by 30%.

PIN CONFIGURATION

Top View

Bottom View

Figure 2. Pin Configuration

Table 3. PIN DEFINITIONS

Pin #	Name	Description
D1	VSEL	**Voltage Select.** When this pin is LOW, V_{OUT} is set by the VSEL0 register. When this pin is HIGH, V_{OUT} is set by the VSEL1 register. This pin in conjunction with the MODE bits in the Control register 02h, will select Forced PWM or Auto PFM/PWM mode of operation. VSEL0 = Auto PFM, and VSEL1 = FPWM. The VSEL pin has an internal pull−down resistor (250 kW), which is only activated with a logic low.
D2	EN	**Enable.** The device is in Shutdown Mode when this pin is LOW. Device keeps register content when EN pin is LOW. The EN Pin has an internal pull−down resistor (250 kW), which is only activated with a logic low.
E2	SCL	**I²C Serial Clock**
D3	SDA	**I²C Serial Data**
E3	VOUT	**VOUT** sense pin for V_{OUT}. Connect to C_{OUT}.
A3, B3, C2	PGND	**Power Ground.** The low−side MOSFET is referenced to this pin. C_{IN} and C_{OUT} should be returned with a minimal path to these pins.
C3, E1	AGND	**Analog Ground.** All signals are referenced to this pin. Avoid routing high di/dt AC currents through this pin.
A1, B1, C1	VIN	**Power Input Voltage.** Connect to the input power source. Connect to C_{IN} with minimal path.
A2, B2	SW	**Switching Node.** Connect to the inductor.

DISCONTINUED
THIS DEVICE IS NOT RECOMMENDED FOR NEW DESIGN
PLEASE CONTACT YOUR onsemi
REPRESENTATIVE FOR INFORMATION

Table 4. ABSOLUTE MAXIMUM RATINGS

Symbol	Parameter	Parameter	Min	Max	Unit
V_{IN}	Voltage on SW, VIN Pins	IC Not Switching	−0.3	7.0	V
		IC Switching	−0.3	6.5	
	Voltage on EN Pin		−0.3	VIN (Note 3)	
	Voltage on All Other Pins	IC Not Switching	−0.3	VIN (Note 3)	
V_{OUT}	Voltage on VOUT Pin		−0.3	6.5	V
V_{INOV_SLEW}	Maximum Slew Rate of V_{IN} > 6.5V, PWM Switching			100	V/ms
ESD	Human Body Model, ANSI/ESDA/JEDEC JS−001−2012		2000		V
	Charged Device Model per JESD22−C101		1000		
T_J	Junction Temperature		−40	+150	°C
T_{STG}	Storage Temperature		−65	+150	°C
T_L	Lead Soldering Temperature, 10 Seconds			+260	°C

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

3. Lesser of 7V or V_{IN} + 0.3 V.

Table 5. RECOMMENDED OPERATING CONDITIONS

Symbol	Parameter	Min.	Typ.	Max.	Unit
V_{IN}	Supply Voltage Range	2.5		5.5	V
I_{OUT}	Output Current	0		3.0	A
T_A	Operating Ambient Temperature	−40		+85	°C
T_J	Operating Junction Temperature	−40		+125	°C

Functional operation above the stresses listed in the Recommended Operating Ranges is not implied. Extended exposure to stresses beyond the Recommended Operating Ranges limits may affect device reliability.

Table 6. THERMAL PROPERTIES

Symbol	Parameter	Min.	Typ.	Max.	Unit
θ_{JA}	Junction−to−Ambient Thermal Resistance (Note 4)		42		°C/W

4. Junction−to−ambient thermal resistance is a function of application and board layout. This data is simulated with four−layer 2s2p boards with vias in accordance to JESD51− JEDEC standard. Special attention must be paid not to exceed the junction temperature

DISCONTINUED
THIS DEVICE IS NOT RECOMMENDED FOR NEW DESIGN
PLEASE CONTACT YOUR onsemi
REPRESENTATIVE FOR INFORMATION

Table 7. ELECTRICAL CHARACTERISTICS

Minimum and maximum values are at V_{IN} = 3.6 V, T_A = −40°C to +85°C, unless otherwise noted.
Typical values are at T_A = 25°C, V_{IN} = 3.6 V, V_{OUT} = 0.4 V and EN = 1.8 V.

Symbol	Parameter	Condition	Min.	Typ.	Max.	Unit
POWER SUPPLIES						
I_Q	Quiescent Current	I_{LOAD} = 0		50		μA
I_{SD}	H/W Shutdown Supply Current	EN = GND		0.1	3.0	μA
	S/W Shutdown Supply Current	EN = 1.8 V, BUCK_ENx = 0, 2.5 V ≤ V_{IN} ≤ 5.5 V		2	12	μA
V_{UVLO}	Under−Voltage Lockout Threshold	V_{IN} Rising		2.32	2.45	V
V_{UVHYST}	Under−Voltage Lockout Hysteresis			350		mV
EN, VSEL, SDA, SCL						
V_{IH}	HIGH−Level Input Voltage	2.5 V ≤ V_{IN} ≤ 5.5 V	1.1			V
V_{IL}	LOW−Level Input Voltage	2.5 V ≤ V_{IN} ≤ 5.5 V			0.4	V
I_{IN}	Input Bias Current	Input Tied to GND or VIN		0.01	1.00	μA
V_{OUT} REGULATION						
V_{REG}	V_{OUT} DC Accuracy	2.8 V ≤ V_{IN} ≤ 4.8 V, V_{OUT} = 0.4 V, $I_{OUT(DC)}$ = 0 A, Auto Mode	−3		+5	%
		2.8 V ≤ V_{IN} ≤ 4.8 V, V_{OUT} = 0.4 V, $I_{OUT(DC)}$ = 0 A, Forced PWM Mode	−1.5		+1.5	
		2.8 V ≤ V_{IN} ≤ 4.8 V, V_{OUT} from Minimum to Maximum, $I_{OUT(DC)}$ = 0 to 3.0 A, Auto Mode	−4		+6	
POWER SWITCH/PROTECTION						
I_{LIMPK}	P−MOS Peak Current Limit		4.00	4.75	5.50	A
T_{LIMIT}	Thermal Shutdown			150		°C
T_{HYST}	Thermal Shutdown Hysteresis			17		°C
V_{SDWN}	Input OVP Shutdown	Rising Threshold		6.15		V
		Falling Threshold	5.50	5.73		
FREQUENCY CONTROL						
f_{SW}	Oscillator Frequency		2.05	2.40	2.75	MHz
DAC						
	Resolution			7		Bits
	Differential Nonlinearity (Note 5)				0.5	LSB

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.

5. Monotonicity assured by design.

DISCONTINUED
THIS DEVICE IS NOT RECOMMENDED FOR NEW DESIGN
PLEASE CONTACT YOUR onsemi
REPRESENTATIVE FOR INFORMATION

Table 8. SYSTEM CHARACTERISTICS

The following system characteristics are guaranteed by design and are not performed in production testing. Recommended operating conditions, unless otherwise noted, V_{IN} =2.5 V to 5.5 V, T_A = −40°C to +85°C, V_{OUT} =0.4 V.
Typical values are given at T_A = 25°C, V_{IN} =3.6 V. System characteristics are based on circuit per Figure 1.
L = 0.33 mH, DFE201610E−R33M (TOKO), C_{IN} = 1 × 4.7 μF, 10 V, 0603 (1608 metric), C1608X5R1A475K (TDK) and C_{OUT} = 2 × 22 μF (6.3 V, 0603, TDK C1608X5R0J226M080AC) + 4 × 100 μF (6.3 V, 0201, Murata GRM033R60J104KE19D) + 1 × 4.7 μF (6.3 V, 0402, TDK C1005X5R0J475M050BC).

Symbol	Parameter	Condition	Min.	Typ.	Max.	Unit
$LOAD_{REG}$	Load Regulation	I_{OUT} = 0 A to 3 A, Forced PWM Mode		0.05		%/A
$LINE_{REG}$	Line Regulation	2.5 V ≤ V_{IN} ≤ 5.5 V, I_{OUT} =1.5 A		0.09		%/V
V_{OUT_RIPPLE}	Ripple Voltage	I_{OUT} = 20 mA, PFM Mode		16		mV
		I_{OUT} = 700 mA, PFM Mode		5		
ΔV_{OUT_LOAD}	Load Transient	I_{OUT} = 10 mA ⇔ 700 mA, t_R = t_F = 200 ns, V_{OUT} = 0.4 V, Auto Mode		±20		mV
		I_{OUT} = 0 mA ⇔ 800 mA, t_R = t_F = 0.9 μs, V_{IN} = 3.2 V, V_{OUT} = 1.125 V, Auto Mode		±13		
		I_{OUT} = 0 mA ⇔ 800 mA, t_R = t_F = 0.9 μs, V_{IN} = 3.8 V, V_{OUT} = 1.125 V, Auto Mode		±15		
ΔV_{OUT_LINE}	Line Transient	V_{IN} = 3.0 V ⇔ 3.6 V, t_R = t_F = 10 μs, I_{OUT} = 100 mA, Forced PWM Mode		±11		mV
t_{ss}	Soft−Start	EN High to 95% of Target V_{OUT} (0.4 V), I_{OUT} = 200 mA; FAN53528BUC08X		85		μs
t_{delay}	EN Delay	EN High to V_{OUT} Start−to−Rise, V_{OUT} = 0.0 V, I_{OUT} = 0 A; FAN53528EUC48X		5		ms

Table 9. I²C TIMING SPECIFICATIONS

Guaranteed by design.

Symbol	Parameter	Condition	Min.	Typ.	Max.	Unit
f_{SCL}	I²C Clock Frequency	Standard Mode			100	kHz
		Fast Mode			400	kHz
		Fast Mode Plus			1000	
		High−Speed Mode, C_B ≤ 100 pF			3400	
		High−Speed Mode, C_B ≤ 400 pF			1700	
t_{BUF}	Bus−Free Time between STOP and START Conditions	Standard Mode		4.7		μs
		Fast Mode		1.3		
		Fast Mode Plus		0.5		
$t_{HD;STA}$	START or REPEATED START Hold Time	Standard Mode		4		μs
		Fast Mode		600		ns
		Fast Mode Plus		260		
		High−Speed Mode		160		
t_{LOW}	SCL LOW Period	Standard Mode		4.7		μs
		Fast Mode		1.3		
		Fast Mode Plus		0.5		
		High−Speed Mode, C_B ≤ 100 pF		160		ns
		High−Speed Mode, C_B ≤ 400 pF		320		

DISCONTINUED
THIS DEVICE IS NOT RECOMMENDED FOR NEW DESIGN
PLEASE CONTACT YOUR onsemi
REPRESENTATIVE FOR INFORMATION

Table 9. I²C TIMING SPECIFICATIONS (continued)
Guaranteed by design.

Symbol	Parameter	Condition	Min.	Typ.	Max.	Unit
t_{HIGH}	SCL HIGH Period	Standard Mode		4		µs
		Fast Mode		600		ns
		Fast Mode Plus		260		
		High−Speed Mode, $C_B \le 100$ pF		60		
		High−Speed Mode, $C_B \le 400$ pF		120		
$t_{SU;STA}$	Repeated START Setup Time	Standard Mode		4.7		µs
		Fast Mode		600		ns
		Fast Mode Plus		260		
		High−Speed Mode		160		
$t_{SU;DAT}$	Data Setup Time	Standard Mode		250		ns
		Fast Mode		100		
		Fast Mode Plus		50		
		High−Speed Mode		10		
$t_{HD;DAT}$	Data Hold Time	Standard Mode	0		3.45	µs
		Fast Mode	0		900	ns
		Fast Mode Plus	0		450	
		High−Speed Mode, $C_B \le 100$ pF	0		70	
		High−Speed Mode, $C_B \le 400$ pF	0		150	
t_{RCL}	SCL Rise Time	Standard Mode	$20+0.1C_B$		1000	ns
		Fast Mode	$20+0.1C_B$		300	
		Fast Mode Plus	$20+0.1C_B$		120	
		High−Speed Mode, $C_B \le 100$ pF		10	80	
		High−Speed Mode, $C_B \le 400$ pF		20	160	
t_{FCL}	SCL Fall Time	Standard Mode	$20+0.1C_B$		300	ns
		Fast Mode	$20+0.1C_B$		300	
		Fast Mode Plus	$20+0.1C_B$		120	
		High−Speed Mode, $C_B \le 100$ pF		10	40	
		High−Speed Mode, $C_B \le 400$ pF		20	80	
t_{RCL1}	Rise Time of SCL After a REPEATED START Condition and After ACK Bit	High−Speed Mode, $C_B \le 100$ pF		10	80	ns
		High−Speed Mode, $C_B \le 400$ pF		20	160	
t_{RDA}	SDA Rise Time	Standard Mode	$20+0.1C_B$		1000	ns
		Fast Mode	$20+0.1C_B$		300	
		Fast Mode Plus	$20+0.1C_B$		120	
		High−Speed Mode, $C_B \le 100$ pF		10	80	
		High−Speed Mode, $C_B \le 400$ pF		20	160	

DISCONTINUED
THIS DEVICE IS NOT RECOMMENDED FOR NEW DESIGN
PLEASE CONTACT YOUR onsemi
REPRESENTATIVE FOR INFORMATION

Table 9. I²C TIMING SPECIFICATIONS (continued)
Guaranteed by design.

Symbol	Parameter	Condition	Min.	Typ.	Max.	Unit
t_{FDA}	SDA Fall Time	Standard Mode	$20+0.1C_B$		300	ns
		Fast Mode	$20+0.1C_B$		300	
		Fast Mode Plus	$20+0.1C_B$		120	
		High−Speed Mode, $C_B \le 100$ pF		10	80	
		High−Speed Mode, $C_B \le 400$ pF		20	160	
$t_{SU;STO}$	Stop Condition Setup Time	Standard Mode		4		μs
		Fast Mode		600		ns
		Fast Mode Plus		120		
		High−Speed Mode		160		
C_B	Capacitive Load for SDA and SCL				400	pF

TIMING DIAGRAMS

Figure 3. I²C Interface Timing for Fast Plus, Fast, and Slow Modes

= MCS Current Source Pull−up

= R_P Resistor Pull−up

Note A: First rising edge of SCLH after Repeated Start and after each ACK bit.

Figure 4. I²C Interface Timing for High−Speed Mode

DISCONTINUED
THIS DEVICE IS NOT RECOMMENDED FOR NEW DESIGN
PLEASE CONTACT YOUR onsemi
REPRESENTATIVE FOR INFORMATION

TYPICAL CHARACTERISTICS

UNLESS OTHERWISE SPECIFIED, V_{IN} = 3.6 V, V_{OUT} = 0.4 V, AUTO MODE, T_A = 25°C; CIRCUIT AND COMPONENTS ACCORDING TO FIGURE 1 AND TABLE 1.

Figure 5. Efficiency vs. Load Current and Input Voltage, V_{OUT} = 0,4 V, Auto Mode

Figure 6. Efficiency vs. Load Current and Temperature, V_{IN} = 3.6 V, V_{OUT} = 0.4 V, Auto Mode

Figure 7. Output Regulation vs. Load Current and Input Voltage, V_{OUT} = 0.4 V, Auto Mode

Figure 8. Frequency vs. Load Current and Input Voltage, V_{OUT} = 0.65 V, Auto Mode

Figure 9. Quiescent Current vs. Input Voltage and Temperature V_{OUT} = 0.4 V, Auto Mode

Figure 10. Shutdown Current vs. Input Voltage and Temperature

DISCONTINUED
THIS DEVICE IS NOT RECOMMENDED FOR NEW DESIGN
PLEASE CONTACT YOUR onsemi
REPRESENTATIVE FOR INFORMATION

TYPICAL CHARACTERISTICS (continued)

UNLESS OTHERWISE SPECIFIED, V_{IN} = 3.6 V, V_{OUT} = 0.4 V, AUTO MODE, T_A = 25°C; CIRCUIT AND COMPONENTS ACCORDING TO FIGURE 1 AND TABLE 1.

Figure 11. Output Ripple, V_{IN} = 3.6 V, V_{OUT} = 0.65 V, 20 mA Load

Figure 12. Output Ripple, V_{IN} = 3.6 V, V_{OUT} = 0.65 V, 700 mA Load

Figure 13. Line Transient, V_{IN} = 3.0 V ⇔ 3.6 V, V_{OUT} = 0.4 V, 10 µs Edge, 100 mA Load, Forced PWM Mode

Figure 14. Load Transient, V_{IN} = 3.6 V, V_{OUT} = 0.4 V, 10 mA ⇔ 700 mA, 200 ns Edge, Auto Mode

Figure 15. Load Transient, V_{IN} = 3.2 V, V_{OUT} = 1.125 V, 0 mA ⇔ 800 mA, 900 ns Edge, Auto Mode

Figure 16. Load Transient, V_{IN} = 3.8 V, V_{OUT} = 1.125 V, 0 mA ⇔ 800 mA, 900 ns Edge, Auto Mode

DISCONTINUED
THIS DEVICE IS NOT RECOMMENDED FOR NEW DESIGN
PLEASE CONTACT YOUR onsemi
REPRESENTATIVE FOR INFORMATION

TYPICAL CHARACTERISTICS (continued)

UNLESS OTHERWISE SPECIFIED, V_{IN} = 3.6 V, V_{OUT} = 0.4 V, AUTO MODE, T_A = 25°C; CIRCUIT AND COMPONENTS ACCORDING TO FIGURE 1 AND TABLE 1.

Figure 17. Startup, V_{IN} = 3.6 V, V_{OUT} = 0.65 V, 200 mA Load, with 5 ms EN Delay, Auto Mode

DISCONTINUED
THIS DEVICE IS NOT RECOMMENDED FOR NEW DESIGN
PLEASE CONTACT YOUR onsemi
REPRESENTATIVE FOR INFORMATION

OPERATING DESCRIPTION

The FAN53528 is a step−down switching voltage regulator that delivers a programmable output voltage from an input voltage supply of 2.5 V to 5.5 V. Using a proprietary architecture with synchronous rectification, the FAN53528 is capable of delivering 3.0 A at over 80% efficiency. The regulator operates at a nominal frequency of 2.4 MHz at full load, which reduces the value of the external components to 330 nH or 470 nH for the output inductor and 44 pF for the output capacitor. High efficiency is maintained at light load with single−pulse PFM.

An I^2C−compatible interface allows transfers up to 3.4 Mbps. This communication interface can be used to:

- Dynamically reprogram the output voltage in 6.25 mV increments;
- Reprogram the mode to enable or disable PFM;
- Control voltage transition slew rate; or
- Enable/disable the regulator.

Control Scheme

The FAN53528 uses a proprietary non−linear, fixed−frequency PWM modulator to deliver a fast load transient response, while maintaining a constant switching frequency over a wide range of operating conditions. The regulator performance is independent of the output capacitor ESR, allowing for the use of ceramic output capacitors. Although this type of operation normally results in a switching frequency that varies with input voltage and load current, an internal frequency loop holds the switching frequency constant over a large range of input voltages and load currents.

For very light loads, the FAN53528 operates in Discontinuous Current Mode (DCM) single−pulse PFM, which produces low output ripple compared with other PFM architectures. Transition between PWM and PFM is relatively seamless, providing a smooth transition between DCM and CCM Modes.

PFM can be disabled by programming the MODE bits in the CONTROL register in combination with the state of the VSEL pin. See table in the Control Register 02h.

Enable and Soft−Start

When the EN pin is LOW; the IC is shut down, all internal circuits are off, and the part draws very little current. In this state, I^2C can be written to or read from as long as input voltage is above the UVLO. The registers keep the content when the EN pin is LOW. The registers are reset to default values during a Power On Reset (POR). When the OUTPUT_DISCHARGE bit in the Control register is enabled (logic HIGH) and the EN pin is LOW or the BUCK_ENx bit is LOW, an 11 Ω load is connected from VOUT to GND to discharge the output capacitors.

Raising EN while the BUCK_ENx bit is HIGH activates the part and begins the soft−start cycle. For option EUC48X, there is 5 ms delay time from EN HIGH to V_{OUT} start soft−start. And for options FAN53528BUC08X, FAN53528GUC48X and FAN53528DUC40X, there is no EN Delay. During soft−start, the modulator's internal reference is ramped slowly to minimize surge currents on the input and prevent overshoot of the output voltage. Synchronous rectification is inhibited, allowing the IC to start into a pre−charged capacitive load.

Figure 18. EN Delay

If large values of output capacitance are used, the regulator may fail to start. The maximum C_{OUT} capacitance for starting with a heavy constant−current load is approximately:

$$C_{OUTMAX} \approx (I_{LMPK} - I_{LOAD}) \times \frac{320\mu}{V_{OUT}} \quad \text{(eq. 1)}$$

where C_{OUTMAX} is expressed in µF and I_{LOAD} is the load current during soft−start, expressed in A.

If the regulator is at its current limit for 16 consecutive current limit cycles, the regulator shuts down and enters tri−state before reattempting soft−start 1700 µs later. This limits the duty cycle of full output current during soft−start to prevent excessive heating.

The IC allows for software enable of the regulator, when EN is HIGH, through the BUCK_EN bits. BUCK_EN0 and BUCK_EN1 are both initialized HIGH. These options are set after a POR, regardless of the state of the VSEL pin.

Table 10. HARDWARE AND SOFTWARE ENABLE

Pins		BITS			
EN	VSEL	BUCK_EN0	BUCK_EN1	Output	Mode
0	X	X	X	OFF	Shutdown
1	0	0	X	OFF	Shutdown
1	0	1	X	ON	Auto
1	1	X	0	OFF	Shutdown
1	1	X	1	ON	FPWM

VSEL Pin and I²C Programming Output Voltage

The output voltage is set by the NSELx control bits in VSEL0 and VSEL1 registers. The output is given as:

$$V_{OUT} = 0.35\ V + NSELx \times 6.25\ mV \quad \text{(eq. 2)}$$

For example, if NSEL =1010000 (80 decimal), then $V_{OUT} = 0.35 + 0.5 = 0.85$ V.

Output voltage can also be controlled by toggling the VSEL pin LOW or HIGH. VSEL LOW corresponds to VSEL0 and VSEL HIGH corresponds to VSEL1. Upon POR, VSEL0 and VSEL1 are reset to their default voltages.

Transition Slew Rate Limiting

When transitioning from a low to high voltage, the IC can be programmed for one of eight possible slew rates using the SLEW bits in the Control register, as shown in Table 11.

Table 11. TRANSITION SLEW RATE

Decimal	Bin	Slew Rate	
0	000	64.00	mV/µs
1	001	32.00	mV/µs
2	010	16.00	mV/µs
3	011	8.00	mV/µs
4	100	4.00	mV/µs
5	101	2.00	mV/µs
6	110	1.00	mV/µs
7	111	0.50	mV/µs

Transitions from high to low voltage rely on the output load to discharge V_{OUT} to the new set point. Once the high−to−low transition begins, the IC stops switching until V_{OUT} has reached the new set point.

Under−Voltage Lockout (UVLO)

When EN is HIGH, the under−voltage lockout keeps the part from operating until the input supply voltage rises HIGH enough to properly operate. This ensures proper operation of the regulator during startup or shutdown.

Input Over−Voltage Protection (OVP)

When V_{IN} exceeds V_{SDWN} (~6.2 V), the IC stops switching to protect the circuitry from internal spikes above 6.5 V. An internal filter prevents the circuit from shutting down due to noise spikes.

Current Limiting

A heavy load or short circuit on the output causes the current in the inductor to increase until a maximum current threshold is reached in the high−side switch. Upon reaching this point, the high−side switch turns off, preventing high currents from causing damage. 16 consecutive current limit cycles in current limit, cause the regulator to shut down and stay off for about 1700 µs before attempting a restart.

Thermal Shutdown

When the die temperature increases, due to a high load condition and/or high ambient temperature, the output switching is disabled until the die temperature falls sufficiently. The junction temperature at which the thermal shutdown activates is nominally 150°C with a 17°C hysteresis.

Monitor Register (Reg05)

The Monitor register indicates of the regulation state of the IC. If the IC is enabled and is regulating, its value is (1000 0001).

I²C Interface

The serial interface is compatible with Standard, Fast, Fast Plus, and HS Mode I²C Bus® specifications. The SCL line is an input and its SDA line is a bi−directional open−drain output; it can only pull down the bus when

DISCONTINUED
THIS DEVICE IS NOT RECOMMENDED FOR NEW DESIGN
PLEASE CONTACT YOUR onsemi
REPRESENTATIVE FOR INFORMATION

active. The SDA line only pulls LOW during data reads and when signaling ACK. All data is shifted in MSB (bit 7) first.

I²C Slave Address

In hex notation, the slave address assumes a 0 LS Bit. The hex slave address is A0 for FAN53528BUCxxX and A4 for FAN53528DUCxxX, FAN53528EUCxxX, and FAN53528GUCxxX.

Table 12. I²C SLAVE ADDRESS

Option	Hex	Bits							
		7	6	5	4	3	2	1	0
BUCxx	A0	1	0	1	0	0	0	0	R/$\overline{W}$
DUCxx, EUCxx, GUCxx	A4	1	0	1	0	0	1	0	R/$\overline{W}$

Other slave addresses can be assigned. Contact an **onsemi** representative.

Bus Timing

As shown in Figure 19 data is normally transferred when SCL is LOW. Data is clocked in on the rising edge of SCL. Typically, data transitions shortly at or after the falling edge of SCL to allow sufficient time for the data to set up before the next SCL rising edge.

Figure 19. Data Transfer Timing

Each bus transaction begins and ends with SDA and SCL HIGH. A transaction begins with a START condition, which is defined as SDA transitioning from 1 to 0 with SCL HIGH, as shown in Figure 20.

Figure 20. START Bit

A transaction ends with a STOP condition, defined as SDA transitioning from 0 to 1 with SCL high, as shown in Figure 21.

Figure 21. STOP Bit

During a read from the FAN53528, the master issues a REPEATED START after sending the register address and before resending the slave address. The REPEATED START is a 1 to 0 transition on SDA while SCL is HIGH, as shown in Figure 22.

Figure 22. REPEATED START Timing

High−Speed (HS) Mode

The protocols for High−Speed (HS), Low−Speed (LS), and Fast−Speed (FS) Modes are identical; except the bus speed for HS Mode is 3.4 MHz. HS Mode is entered when the bus master sends the HS master code 00001XXX after a START condition (Figure 20). The master code is sent in Fast or Fast−Plus Mode (less than 1 MHz clock); slaves do not ACK this transmission.

The master generates a REPEATED START condition (Figure 22) that causes all slaves on the bus to switch to HS Mode. The master then sends I²C packets, as described above, using the HS Mode clock rate and timing.

The bus remains in HS Mode until a STOP bit (Figure 21) is sent by the master. While in HS Mode, packets are separated by REPEATED START conditions (Figure 22).

Read and Write Transactions

The following figures outline the sequences for data read and write. Bus control is signified by the shading of the packet, defined as:

- Master Drives Bus and
- Slave Drives Bus

All addresses and data are MSB first.

Table 13. I²C BIT DEFINITIONS FOR FIGURE 23 AND FIGURE 24

Symbol	Definition
S	START, see Figure 20
P	STOP, see Figure 21
A	ACK. The slave drives SDA to 0 to acknowledge the preceding packet.
$\overline{A}$	NACK. The slave sends a 1 to NACK the preceding packet.
R	REPEATED START, see Figure 22

DISCONTINUED
THIS DEVICE IS NOT RECOMMENDED FOR NEW DESIGN
PLEASE CONTACT YOUR onsemi
REPRESENTATIVE FOR INFORMATION

Figure 23. Write Transaction

Figure 24. Write Transaction Followed by a Read Transaction

REGISTER DESCRIPTION

Table 14. REGISTER MAP

Hex Address	Name	Function	Binary	Hex
00	VSEL0	Controls V_{OUT} settings when VSEL pin = LOW	1XXXXXXX	XX
01	VSEL1	Controls V_{OUT} settings when VSEL pin = HIGH	1XXXXXXX	XX
02	CONTROL	Determines whether V_{OUT} output discharge is enabled and a[illegible] the slew rate of positive transitions	10000010	82
03	ID1	Read−only register identifies vendor and chip	10000001	81
04	ID2	Read−only register identifies die revi[illegible]	00001000	08
05	MONITOR	Indicates device status	00000000	00

Table 15. BIT DEFINITIONS

The following table defines the operation or e[illegible]h regis[illegible]r b[illegible]. Bold indicates power−on defa[illegible]it values.

Bit	Name	T[illegible]pe	[illegible]e	Description
VSEL0				**Register Address: 00**
7	BUCK_[illegible]0	[illegible]/W	**1**	Software buck enable. When EN pin is LOW, the regulator is off. When EN pin is HIGH, BUCK_EN bit takes precedent.
6:0	NSE[illegible]	R/W	**XXX XXXX**	Sets V_{OUT} value from 0.35 to 1.14375 V (see eq. 2).
VSEL1				**Register Address: 01**
7	BUCK_EN1	R/W	**1**	Software buck enable. When EN pin is LOW, the regulator is off. When EN pin is HIGH, BUCK_EN bit takes precedent.
6:0	NSEL1	R/W	**XXX XXXX**	Sets V_{OUT} value from 0.35 to 1.14375 V (see eq. 2).
CONTROL				**Register Address: 02**
7	OUTPUT_DISCHARGE	R/W	0	When the regulator is disabled, V_{OUT} is not discharged.
			1	When the regulator is disabled, V_{OUT} discharges through an internal pull−down.
6:4	SLEW	R/W	**000** −111	Sets the slew rate for positive voltage transitions (see Table 11)
3	Reserved		**0**	Always reads back 0.
2	RESET	R/W	**0**	Setting to 1 resets all registers to default values. Always reads back 0.
1:0	MODE	R/W	**10**	In combination with the VSEL pin, these two bits set the operation of the buck to be either in Auto−PFM/PWM Mode during light load or Forced PWM mode. See table below. Mode of Operation **VSEL Pin Binary Operation** Low X0 Auto PFM/PWM Low X1 Forced PWM High 0X Auto PFM/PWM High 1X Forced PWM

DISCONTINUED
THIS DEVICE IS NOT RECOMMENDED FOR NEW DESIGN
PLEASE CONTACT YOUR onsemi
REPRESENTATIVE FOR INFORMATION

Table 15. BIT DEFINITIONS (continued)

The following table defines the operation or each register bit. Bold indicates power−on default values.

Bit	Name	Type	Value	Description
ID1				**Register Address: 03**
7:5	VENDOR	**R**	**100**	Signifies **onsemi** as the IC vendor.
4	Reserved	**R**	**0**	Always reads back 0.
3:0	DIE_ID	**R**	**0001**	DIE ID
ID2				**Register Address: 04**
7:4	Reserved	**R**	**0000**	Always reads back 0000.
3:0	DIE_REV	**R**	**1000**	FAN53528 Die Revision
MONITOR				**Register Address: 05**
7	PGOOD	**R**	**0**	1: Buck is enabled and soft−start is completed.
6	UVLO	**R**	**0**	1: Signifies the VIN is less than the UVLO threshold.
5	OVP	**R**	**0**	1: Signifies the VIN is greater than the OVP threshold.
4	POS	**R**	**0**	1: Signifies a positive voltage transition is in progress and the output voltage has not yet reached its new setpoint. This bit is also set during IC soft−start.
3	NEG	**R**	**0**	1: Signifies a negative voltage transition is in progress and the output voltage has not yet reached its new setpoint.
2	RESET_STAT	**R**	**0**	1: Indicates that a register reset was performed. This bit is cleared after register 5 is read.
1	OT	**R**	**0**	1: Signifies the thermal shutdown is active.
0	BUCK_STATUS	**R**	**0**	1: Buck enabled; 0: buck disabled.

DISCONTINUED
THIS DEVICE IS NOT RECOMMENDED FOR NEW DESIGN
PLEASE CONTACT YOUR onsemi
REPRESENTATIVE FOR INFORMATION

APPLICATION INFORMATION

Selecting the Inductor

The output inductor must meet both the required inductance and the energy−handling capability of the application. The inductor value affects the average current limit, the output voltage ripple, and the efficiency.

The ripple current (ΔI) of the regulator is:

$$\Delta I \approx \frac{V_{OUT}}{V_{IN}} \times \left(\frac{V_{IN} - V_{OUT}}{L \times f_{SW}}\right) \quad \text{(eq. 3)}$$

The maximum average load current, $I_{MAX(LOAD)}$, is related to the peak current limit, $I_{LIM(PK)}$, by the ripple current such that:

$$I_{MAX(LOAD)} = I_{LIM(PK)} - \frac{\Delta I}{2} \quad \text{(eq. 4)}$$

The FAN53528 is optimized for operation with L=330 nH, but is stable with inductances up to 1.0 µH (nominal). The inductor should be rated to maintain at least 80% of its value at $I_{LIM(PK)}$. Failure to do so decreases the amount of DC current the IC can deliver.

Efficiency is affected by the inductor DCR and inductance value. Decreasing the inductor value for a given physical size typically decreases the DCR; but since ΔI increases, the RMS current increases, as do core and skin−effect losses:

$$I_{RMS} = \sqrt{I_{OUT(DC)}^{2} + \frac{\Delta I^2}{12}} \quad \text{(eq. 5)}$$

The increased RMS current produces higher losses through the $R_{DS(ON)}$ of the IC MOSFETs and the inductor ESR.

Increasing the inductor value produces lower RMS currents, but degrades transient response. For a given physical inductor size, increased inductance usually results in an inductor with lower saturation current.

Table 16. EFFECTS OF INDUCTOR VALUE (FROM 330 nH RECOMMENDED) ON REGULATOR PERFORMANCE

$I_{MAX(LOAD)}$	ΔV_{OUT} (eq. 7)	Transient Response
Increase	Decrease	Degraded

Inductor Current Rating

The current−limit circuit can allow substantial peak currents to flow through L1 under worst−case conditions. If it is possible for the load to draw such currents, the inductor should be capable of sustaining the current or failing in a safe manner.

For space−constrained applications, a lower current rating for L1 can be used. The FAN53528 may still protect these inductors in the event of a short circuit, but may not be able to protect the inductor from failure if the load is able to draw higher currents than the DC rating of the inductor. Refer to Table 2 for the recommended inductors.

Output Capacitor and V_{OUT} Ripple

If space is at a premium, 0603 capacitors may be used.

Increasing C_{OUT} has negligible effect on loop stability and can be increased to reduce output voltage ripple or to improve transient response. Output voltage ripple, ΔV_{OUT}, is calculated by:

$$\Delta V_{OUT} = \Delta I_L \left[\frac{f_{SW} \times C_{OUT} \times ESR^2}{2 \times D \times (1 - D)} + \frac{1}{8 \times f_{SW} \times C_{OUT}} \right] \quad \text{(eq. 6)}$$

where C_{OUT} is the effective output capacitance.

The capacitance of C_{OUT} decreases at higher output voltages, which results in higher ΔV_{OUT}. Equation 6 is only valid for CCM operation, which occurs in PWM Mode.

The FAN53528 can be used with either 2 x 22 µF (0603) or 2 x 47 µF (0603) output capacitor configuration. If a tighter ripple and transient specification is need from the FAN53528, then the 2 x 47 µF is recommended.

The lowest ΔV_{OUT} is obtained when the IC is in PWM Mode and, therefore, operating at 2.4 MHz. In PFM Mode, f_{SW} is reduced, causing ΔV_{OUT} to increase.

ESL Effects

The Equivalent Series Inductance (ESL) of the output capacitor network should be kept low to minimize the square−wave component of output ripple that results from the division ratio C_{OUT} ESL and the output inductor (L_{OUT}). The square−wave component due to the ESL can be estimated as:

$$\Delta V_{OUT(SQ)} \approx V_{IN} \times \frac{ESL_{COUT}}{L1} \quad \text{(eq. 7)}$$

A good practice to minimize this ripple is to use multiple output capacitors to achieve the desired C_{OUT} value. For example, to obtain C_{OUT} = 20 µF, a single 22 µF 0805 would produce twice the square wave ripple as two × 10 µF 0805.

To minimize ESL, try to use capacitors with the lowest ratio of length to width. 0805 s have lower ESL than 1206 s. If low output ripple is a chief concern, some vendors produce 0508 capacitors with ultra-low ESL. Placing additional small−value capacitors near the load also reduces the high−frequency ripple components.

Input Capacitor

The ceramic input capacitors should be placed as close as possible between the VIN and PGND pins to minimize the parasitic inductance. If a long wire is used to bring power to the IC, additional "bulk" capacitance (electrolytic or tantalum) should be placed between CIN and the power source lead to reduce under−damped ringing that can occur between the inductance of the power source leads and C_{IN}.

The effective C_{IN} capacitance value decreases as V_{IN} increases due to DC bias effects. This has no significant impact on regulator performance.

Thermal Considerations

Heat is removed from the IC through the solder bumps to the PCB copper. The junction−to−ambient thermal resistance (θ_{JA}) is largely a function of the PCB layout (size, copper weight, and trace width) and the temperature rise from junction to ambient (ΔT).

For the FAN53528, θ_{JA} is 42°C/W when mounted on its four−layer with vias evaluation board in still air with 2 oz. outer layer copper weight and 1 oz. inner layer.

For long−term reliable operation, the junction temperature (T_J) should be maintained below 125°C.

To calculate maximum operating temperature (<125°C) for a specific application:

1. Use efficiency graphs to determine efficiency for the desired V_{IN}, V_{OUT}, and load conditions.
2. Calculate total power dissipation using:

$$P_T = V_{OUT} \times I_{LOAD} \times \left(\frac{1}{\eta} - 1\right) \quad \text{(eq. 8)}$$

3. Estimate inductor copper losses using:

$$P_L = I_{LOAD}^2 \times DCR_L \quad \text{(eq. 9)}$$

4. Determine IC losses by removing inductor losses (step 3) from total dissipation:

$$P_{IC} = P_T - P_L \quad \text{(eq. 10)}$$

5. Determine device operating temperature:

$$\Delta T = P_{IC} \times \theta_{JA} \qquad T_{IC} = T_A + \Delta T \quad \text{(eq. 11)}$$

and

note that the $R_{DS(ON)}$ of the power MOSFETs increases linearly with temperature at about 1.4%/°C. This causes the efficiency (η) to degrade with increasing die temperature.

Layout Recommendations

1. The input capacitor (C_{IN}) should be connected as close as possible to the VIN and GND pins. Connect to VIN and GND using only top metal. Do not route through vias.
2. Place the inductor (L) as close as possible to the IC. Use short wide traces for the main current paths.
3. The output capacitor (C_{OUT}) should be placed as close as possible to the IC. Connection to GND should be on top metal. Feedback signal connection to VOUT should be routed away from noisy components and traces (e.g. SW line). For remote sensing application, place one or all output capacitors near the load and if there are also output capacitors placed near the inductor, the maximum trace resistance between the inductor and the load should not exceed 30 mΩ.

DISCONTINUED
THIS DEVICE IS NOT RECOMMENDED FOR NEW DESIGN
PLEASE CONTACT YOUR onsemi
REPRESENTATIVE FOR INFORMATION

Figure 25. Guidance for Layer 1

DISCONTINUED
THIS DEVICE IS NOT RECOMMENDED FOR NEW DESIGN
PLEASE CONTACT YOUR onsemi
REPRESENTATIVE FOR INFORMATION

Figure 26. Layer 2

Figure 27. Layer 3

Figure 28. Layer 4

Figure 29. Remote Sensing Schematic

DISCONTINUED
THIS DEVICE IS NOT RECOMMENDED FOR NEW DESIGN
PLEASE CONTACT YOUR onsemi
REPRESENTATIVE FOR INFORMATION

Table 17. PRODUCT SPECIFIC DIMENSIONS

D	E	X	Y
2.015 ± 0.03 mm	1.310 ± 0.03 mm	0.255 mm	0.2075 mm

onsemi is licensed by Philips Corporation to carry the I^{2}C Bus Protocol.
ARM is a registered trademark of ARM Limited (or its subsidiaries) in the EU and/or elsewhere.
Tegra is a trademark of NVIDIA Corporation.
OMAP is a trademark and brand of Texas Instruments Incorporated.
NovaThor is a trademark of ST−Ericsson.
ARMADA is a trademark of Emergency Technology, Inc.
Krait is a trademark of Qualcomm Incorporated.

WLCSP15 2.015x1.31x0.586
CASE 567QS
ISSUE O

DATE 31 OCT 2016

TOP VIEW

RECOMMENDED LAND PATTERN
(NSMD TYPE)

SIDE VIEWS

BOTTOM VIEW

NOTES

A. NO JEDEC REGISTRATION APPLIES.
B. DIMENSIONS ARE IN MILLIMETERS.
C. DIMENSIONS AND TOLERANCE PER ASME Y14.5 - 2009.
D. DATUM C IS DEFINED BY THE SPHERICAL CROWNS OF THE BALLS.
E. PACKAGE NOMINAL HEIGHT IS 586 ± 39 MICRONS (547-625 MICRONS).
F. FOR DIMENSIONS D,E,X, AND Y SEE PRODUCT DATASHEET.

DOCUMENT NUMBER:	**98AON13347G**	Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red.
DESCRIPTION:	**WLCSP15 2.015x1.31x0.586**	**PAGE 1 OF 1**

onsemi and onsemi are trademarks of Semiconductor Components Industries, LLC dba **onsemi** or its subsidiaries in the United States and/or other countries. **onsemi** reserves the right to make changes without further notice to any products herein. **onsemi** makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. **onsemi** does not convey any license under its patent rights nor the rights of others.

onsemi, onsemi, and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "**onsemi**" or its affiliates and/or subsidiaries in the United States and/or other countries. **onsemi** owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of **onsemi**'s product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent−Marking.pdf. **onsemi** reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as−is" and **onsemi** makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using **onsemi** products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by **onsemi**. "Typical" parameters which may be provided in **onsemi** data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. **onsemi** does not convey any license under any of its intellectual property rights nor the rights of others. **onsemi** products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use **onsemi** products for any such unintended or unauthorized application, Buyer shall indemnify and hold **onsemi** and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that **onsemi** was negligent regarding the design or manufacture of the part. **onsemi** is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

ADDITIONAL INFORMATION

TECHNICAL PUBLICATIONS:
Technical Library: www.onsemi.com/design/resources/technical−documentation
onsemi Website: www.onsemi.com

ONLINE SUPPORT: www.onsemi.com/support
For additional information, please contact your local Sales Representative at
www.onsemi.com/support/sales