



Image Sensor Color Correction

ON Semiconductor®

www.onsemi.com

Introduction

This reference document will describe the basic process to obtain colors from a digital image sensor.

Basic Process to Obtain Color Images from Digital Image Sensors

CCD and CMOS solid-state image sensors contain an array of photosensitive elements called pixels. The pixels collect light from a scene and convert it into electrical signal. The signal is then digitized and processed. Digital cameras use CCD or CMOS image sensors to capture images.

TECHNICAL NOTE

Silicon-based image sensors are sensitive to light with wavelengths from up to 1,050 nm, as shown in Figure 1.




Figure 1. Spectral Response of a CMOS Image Sensor

Images captured by a solid state image sensor are, therefore, monochrome in nature. To generate a color image, three primary colors (Red, Green, Blue) are required for each pixel. Before the invention of color image sensors, the color image was created by superimposing three identical images with three different primary colors. These images were captured by placing a color filter in front of the sensor, allowing a certain bandwidth of the visible light to pass through.

a scene from a single image capture. This specific CFA pattern is now known as a “Bayer pattern” and is used in most of the world’s color digital camera systems.

Bayer Color Filter Array and Color Interpolation

In early 1970s, Bryce Bayer realized that an image sensor with a color filter array (CFA) pattern like that shown in Figure 2 would allow the reconstruction of all the colors of

G1	R	G1	R
B	G2	B	G2
G1	R	G1	R
B	G2	B	G2

Figure 2. Bayer CFA Patterns

After capture, the signal of each pixel is read out sequentially; digitized and stored in memory. The original data for each pixel only contains information about one color, depending on which filter is positioned over that pixel. However, information for all three primary colors is needed to construct a color image. The missing information is extracted based on the information gathered by the neighboring pixels. This is called “color interpolation”.

There are a variety of interpolation methods, such as “Nearest Neighbor Interpolation”, “Bilinear Interpolation”, and “Bi-cubic Interpolation”, etc. These simple methods are described in the literature. The quality of the final image depends in large part on which algorithm is used. For this reason many camera manufacturers consider their best color interpolation algorithms to be trade secrets and do not publish them.




Figure 3. Spectral Response of a CMOS Sensor with RGB CFA

The colors values obtained through the color interpolation process are called native colors. Due to the spectral characteristics of the optics (lens, filters) used in the system, the lighting conditions (such as daylight, fluorescent, or tungsten) of the scene, and the characteristics of the color filters of the sensor, the native RGB data may not provide a faithful color rendition.

Color Correction Matrix (CCM)

For this reason an additional step called color correction is required. In most cases, the native spectral RGB is first converted into a standard R’G’B’ (sRGB, for example) color space by a 3x3 color correction matrix, shown in Figure 4. sRGB is the standard color format for most digital imaging input and output devices.

$$\begin{matrix}
 b_{11} & b_{12} & b_{13} & R & R' \\
 b_{21} & b_{22} & b_{23} & G & G' \\
 b_{31} & b_{32} & b_{33} & B & B'
 \end{matrix} \bullet G = G'$$

Figure 4. Color Correction Matrix for RGB → R’G’B’

Generating the correct values for the 3x3 color matrix requires a great deal of knowledge in image science. The spectral response of the CCD is different from the spectral response of an output device. In turn, the spectral response of the output device is different from the spectral response of the human eye. Therefore, “perfect” color reproduction is


not possible, because we do not have the spectral information for the scene. ON Semiconductor will provide analytical matrix coefficients (a_{ij}, b_{ij}) to its customers given the characteristic of the optics and a certain lighting condition for a specific sensor. This matrix minimizes the color error for the range of hues of which the eye is most critical. The native primaries can then be converted to the color space to match the output device for optimal color reproduction.

Many imaging systems function more efficiently by using a luminance/color-difference color space, such as YUV or YC_rC_b. This allows the system to process the brightness and color signals separately. Figure 5 shows the color conversion matrix from the standard sRGB color space and the YC_rC_b color space for JPEG compression.

$$\begin{matrix}
 + 0.289 & + 0.587 & + 0.114 & R' & Y \\
 - 0.169 & - 0.441 & + 0.500 & G' & C_b \\
 + 0.500 & - 0.418 & - 0.081 & B' & C_r
 \end{matrix}$$

Figure 5. Color Conversion Matrix for R’G’B’ → YC_rC_b

Today, the conversion matrix operation is generally performed in a digital signal processor. After the processing, the data can be converted back to a color space suitable for any output device.

ON Semiconductor and the  are registered trademarks of Semiconductor Components Industries, LLC (SCILLC) or its subsidiaries in the United States and/or other countries. SCILLC owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of SCILLC's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. SCILLC reserves the right to make changes without further notice to any products herein. SCILLC makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does SCILLC assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in SCILLC data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. SCILLC does not convey any license under its patent rights nor the rights of others. SCILLC products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the SCILLC product could create a situation where personal injury or death may occur. Should Buyer purchase or use SCILLC products for any such unintended or unauthorized application, Buyer shall indemnify and hold SCILLC and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that SCILLC was negligent regarding the design or manufacture of the part. SCILLC is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor
19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA
Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada
Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada
Email: orderlit@onsemi.com

N. American Technical Support: 800-282-9855 Toll Free
USA/Canada
Europe, Middle East and Africa Technical Support:
Phone: 421 33 790 2910
Japan Customer Focus Center
Phone: 81-3-5817-1050

ON Semiconductor Website: www.onsemi.com
Order Literature: <http://www.onsemi.com/orderlit>
For additional information, please contact your local
Sales Representative