

Product Overview

MUN2112: PNP Bipolar Digital Transistor (BRT)

For complete documentation, see the data sheet.

This series of digital transistors is designed to replace a single device and its external resistor bias network. The Bias Resistor Transistor (BRT) contains a single transistor with a monolithic bias network consisting of two resistors; a series base resistor and a base-emitter resistor. The BRT eliminates these individual components by integrating them into a single device. The use of a BRT can reduce both system cost and board space.

Features

- Simplifies Circuit Design
- Reduces Board Space
- Reduces Component Count
- S and NSV Prefix for Automotive and Other Applications Requiring Unique Site and Control Change Requirements; AEC-Q101 Qualified and PPAP Capable
- These Devices are PbFree, Halogen Free/BFR Free and are RoHS Compliant

Part Electrical Specifications

| Product | Compliance | Status | Polarity | I_C Continuous (A) | V_{BRICE0} Min (V) | h_{FE} Min | R1 (k Ω) | R2 (k Ω) | R1/R2 Typ | $V_{i(off)}$ Max (V) | $V_{i(on)}$ Min (V) | Package Type |
|---------------|---|--------|----------|----------------------|----------------------|--------------|------------------|------------------|-----------|----------------------|---------------------|--------------|
| MUN2112T1G | Pb-free Halide free | Active | PNP | 0.1 | 50 | 60 | 22 | 22 | 1 | 0.8 | 2.5 | SC-59-3 |
| NSVMUN2112T1G | AEC Qualified PPAP Capable Pb-free Halide free | Active | PNP | 0.1 | 50 | 60 | 22 | 22 | 1 | 0.8 | 2.5 | SC-59-3 |
| SMUN2112T1G | AEC Qualified PPAP Capable Pb-free Halide free | Active | PNP | 0.1 | 50 | 60 | 22 | 22 | 1 | 0.8 | 2.5 | SC-59-3 |

For more information please contact your local sales support at www.onsemi.com.

Created on: 5/25/2019