Ultrafast Dual Diode 30 A, 200 V

RURG3020CC

Description


The RURG3020CC is an ultrafast dual diode with low forward voltage drop. This device is intended for use as freewheeling and clamping diodes in a variety of switching power supplies and other power switching applications. It is specially suited for use in switching power supplies and industrial application.

Features

- Ultrafast Recovery $t_{rr} = 50 \text{ ns} (@ I_F = 30 \text{ A})$
- Max Forward Voltage, $V_F = 1.0 V (@ T_C = 25^{\circ}C)$
- Reverse Voltage, V_{RRM} = 200 V
- Avalanche Energy Rated
- This Device is Pb-Free and is RoHS Compliant

Applications

- Switching Power Supplies
- Power Switching Circuits
- General Purpose



See detailed ordering and shipping information on page 2 of this data sheet.

RURG3020CC

ABSOLUTE MAXIMUM RATINGS (Per Leg) (T_C = 25° C)

Parameter	Symbol	Ratings	Unit
Peak Repetitive Reverse Voltage	V _{RRM}	200	V
Working Peak Reverse Voltage	V _{RWM}	200	V
DC Blocking Voltage	V _R	200	V
Average Rectified Forward Current (Per Leg) ($T_C = 145^{\circ}C$)	I _{F(AV)}	30	А
Repetitive Peak Surge Current (Square Wave, 20 kHz)	I _{FRM}	70	А
Nonrepetitive Peak Surge Current (Halfwave, 1 Phase, 60 Hz)	I _{FSM}	325	А
Maximum Power Dissipation	PD	125	W
Avalanche Energy (See Figures 7 and 8)	E _{AVL}	20	mJ
Operating and Storage Temperature	T _{STG} , T _J	-65 to 175	°C

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

PACKAGE MARKING AND ORDERING INFORMATION

Device	Device Marking	Package	Shipping	
RURG3020CC	RURG3020C	TO-247-3LD	450 / Tube	

ELECTRICAL SPECIFICATION (Per Leg) (T_C = 25°C, unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Тур	Max	Unit
Instantaneous Forward Voltage (Pulse Width = 300 μ s, Duty Cycle = 2%)	V _F	I _F = 30 A	-	-	1.0	V
		I _F = 30 A, T _C = 150°C	-	-	0.85	V
Instantaneous Reverse Current	I _R	V _R = 200 V	-	-	250	μΑ
		$V_{R} = 200 \text{ V}, \text{ T}_{C} = 150^{\circ}\text{C}$	-	-	1	mA
Reverse Recovery Time (See Figure 6) Summation of t_{a} + t_{b}	t _{rr}	$I_F = 1 \text{ A}, \text{ d}I_F/\text{d}t = 100 \text{ A}/\mu\text{s}$	-	-	45	ns
		$I_F = 30 \text{ A}, \text{ d}I_F/\text{d}t = 100 \text{ A}/\mu\text{s}$	-	-	50	ns
Time to Reach Peak Reverse Current (See Figure 6)	t _a	I_F = 30 A, d I_F /dt = 100 A/ μ s	-	20	-	ns
Time from Peak $\rm I_{RM}$ to Projected Zero Crossing of $\rm I_{RM}$ Based on a Straight Line from Peak $\rm I_{RM}$ through 25% of $\rm I_{RM}$ (See Figure 6)	t _b	I _F = 30 A, dI _F /dt = 100 A/μs	-	15	-	ns
Thermal Resistance Junction to Case	$R_{\theta JC}$		-	-	1.2	°C/W

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.

RURG3020CC

TYPICAL PERFORMANCE CURVES




Figure 2. Reverse Current vs. Reverse Voltage





Figure 3. $t_{rr},\,t_a$ and t_b Curves vs. Forward Current



RURG3020CC

TEST CIRCUITS AND WAVEFORMS







Figure 7. Avalanche Energy Test Circuit








Figure 8. Avalanche Current and Voltage Waveforms



www.onsemi.com 4





ON Semiconductor and use trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. ON Semiconductor does not convey any license under its patent rights nor the rights of others.

onsemi, ONSEMI, and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries. onsemi owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of onsemi's product/patent coverage may be accessed at <u>www.onsemi.com/site/pdf/Patent_Marking.pdf</u>. onsemi reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and onsemi makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or indental damages. Buyer is responsible for its products and applications using onsemi products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by onsemi. "Typical" parameters which may be provided in onsemi data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. onsemi does not convey any license under any of its intellectual property rights nor the rights of others. onsemi products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification. Buyer shall indemnify and hold onsemi and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs,

ADDITIONAL INFORMATION

TECHNICAL PUBLICATIONS:

Technical Library: www.onsemi.com/design/resources/technical-documentation onsemi Website: www.onsemi.com

ONLINE SUPPORT: <u>www.onsemi.com/support</u> For additional information, please contact your local Sales Representative at <u>www.onsemi.com/support/sales</u>