

**DATE 04 MAY 2004** 



## 10 PIN FLIP-CHIP CASE 489AA **ISSUE A**



SCALE 4:1

NOTES:

- 1. DIMENSIONING AND TOLERANCING PER ASME Y14.5M, 1994. 2. CONTROLLING DIMENSION:
- MILLIMETERS.
  3. COPLANARITY APPLIES TO SPHERICAL CROWNS OF SOLDER BALLS.

|     | MILLIMETERS |       |  |
|-----|-------------|-------|--|
| DIM | MIN         | MAX   |  |
| Α   |             | 0.650 |  |
| A1  | 0.210       | 0.270 |  |
| A2  | 0.280       | 0.380 |  |
| D   | 1.965 BSC   |       |  |
| Е   | 1.465 BSC   |       |  |
| b   | 0.250       | 0.350 |  |
| e   | 0.500 BSC   |       |  |
| D1  | 1.500 BSC   |       |  |
| E1  | 1.000 BSC   |       |  |

## **GENERIC MARKING DIAGRAM\***




= Specific Device Code XXXX

YY = Year WW = Work Week

\*This information is generic. Please refer to device data sheet for actual part marking. Pb-Free indicator, "G" or microdot " ■", may or may not be present.

| 4 X            | <b>←</b> D→ | A B          |
|----------------|-------------|--------------|
| □ 0.10 C       |             |              |
| PIN ONE CORNER | 0           | <b>↑ E ↓</b> |

|           |          | ⊢A1        |                 |
|-----------|----------|------------|-----------------|
| // 0.10 C | <b>\</b> | ↓          |                 |
| <u> </u>  | A2 ·     | A          |                 |
| ○ 0.075 C | Ť ,      | <b>† †</b> | C SEATING PLANE |



| DOCUMENT NUMBER: | 98AON12946D      | Electronic versions are uncontrolled except when accessed directly from the Document Repository.<br>Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red. |             |
|------------------|------------------|---|-------------|
| DESCRIPTION:     | 10 PIN FLIP-CHIP |   | PAGE 1 OF 1 |

onsemi and ONSEMI are trademarks of Semiconductor Components Industries, LLC dba onsemi or its subsidiaries in the United States and/or other countries. onsemi reserves the right to make changes without further notice to any products herein. onsemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. onsemi does not convey any license under its patent rights nor the rights of others.