
ON Semiconductor

Is Now

Onsemi

To learn more about onsemi[™], please visit our website at <u>www.onsemi.com</u>

onsemi and ONSEMI. and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries. onsemi owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of onsemi product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. onsemi reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and onsemi makes no warranty, representation or guarantee regarding the accuracy of the information, product factures, availability, functionality, or suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using onsemi products, including compliance with all laws, regulations and asfety requirements or standards, regardless of any support or applications information provided by onsemi. "Typical" parameters which may be provided in onsemi data sheets and/or by customer's technical experts. onsemi products and actal performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. onsemi products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use onsemi products for any such unintended or unauthorized application, Buyer shall indemnify and hold onsemi and its officers, employees, subsidiari



FUNCTIONAL DESCRIPTION


The MC74AC352/74ACT352 is a dual 4-input multiplexer. It selects two bits of data from up to four sources under the control of the common Select inputs (S₀, S₁). The two 4-input multiplexer circuits have individual active LOW Enables (\overline{E}_a , \overline{E}_b) which can be used to strobe the outputs independently. When the Enables (\overline{E}_a , \overline{E}_b) are HIGH, the corresponding outputs (\overline{Z}_a , \overline{Z}_b) are forced HIGH.

The logic equations for the outputs are shown below:

$$\overline{Z}_{a} = \overline{E}_{a} \cdot (|I_{0a} \cdot \overline{S}_{1} \cdot \overline{S}_{0} + |I_{1a} \cdot \overline{S}_{1} \cdot S_{0} + |I_{2a} \cdot S_{1} \cdot \overline{S}_{0} + |I_{3a} \cdot S_{1} \cdot S_{0})$$

$$\overline{Z}_{b} = \overline{E}_{b} \cdot (|I_{0b} \cdot \overline{S}_{1} \cdot \overline{S}_{0} + |I_{1b} \cdot \overline{S}_{1} \cdot S_{0} + |I_{2b} \cdot S_{1} \cdot S_{0})$$

The MC74AC352/74ACT352 can be used to move data from a group of registers to a common output bus. The particular register from which the date came would be determined by the state of the Select inputs. A less obvious application is as a function generator. The MC74AC352/ 74ACT352 can generate two functions of three variables. This is useful for implementing highly irregular random logic.



operations and should not be used to estimate propagation delays.

MAXIMUM RATINGS*

Symbol	Parameter	Value	Unit
V _{CC}	DC Supply Voltage (Referenced to GND)	–0.5 to +7.0	V
V _{in}	DC Input Voltage (Referenced to GND)	–0.5 to V _{CC} +0.5	V
V _{out}	DC Output Voltage (Referenced to GND)	–0.5 to V _{CC} +0.5	V
l _{in}	DC Input Current, per Pin	±20	mA
l _{out}	DC Output Sink/Source Current, per Pin	±50	mA
I _{CC}	DC V_{CC} or GND Current per Output Pin	±50	mA
T _{stg}	Storage Temperature	−65 to +150	°C

* Maximum Ratings are those values beyond which damage to the device may occur. Functional operation should be restricted to the Recommended Operating Conditions.

RECOMMENDED OPERATING CONDITIONS

	Parameter		Min	Тур	Max	Unit		
		'AC	2.0	5.0	6.0	v		
V _{CC}	Supply Voltage	′ACT	4.5	5.0	5.5	v		
V _{in} , V _{out}	DC Input Voltage, Output Voltage (Ref. to GND)		0		V _{CC}	V		
		V _{CC} @ 3.0 V		150	1			
t _r , t _f	Input Rise and Fall Time (Note 1) 'AC Devices except Schmitt Inputs	V _{CC} @ 4.5 V		40)	ns/V		
		V _{CC} @ 5.5 V	V.C	25				
	Input Rise and Fall Time (Note 2)	V _{CC} @ 4.5 V		10				
t _r , t _f	ACT Devices except Schmitt Inputs	V _{CC} @ 5.5 V		8.0		ns/V		
TJ	Junction Temperature (PDIP)	603			140	°C		
T _A	Operating Ambient Temperature Range	2 0	-40	25	85	°C		
I _{ОН}	Output Current — High		~		-24	mA		
I _{OL}	Output Current — Low	2.00			24	mA		
	Output Current — Low to 70% V _{CC} ; see individual Data Sheets for devices that differ from V to 2.0 V; see individual Data Sheets for devices that differ from	the typical input rise						

DC CHARACTERISTICS

			74AC		74AC			
Symbol	Parameter	V _{CC} (V)	T _A = +25°C		T _A = -40°C to +85°C	Unit	Conditions	
			Тур	Guar	anteed Limits			
V _{IH}	Minimum High Level Input Voltage	3.0 4.5 5.5	1.5 2.25 2.75	2.1 3.15 3.85	2.1 3.15 3.85	V	V_{OUT} = 0.1 V or V_{CC} – 0.1 V	
V _{IL}	Maximum Low Level Input Voltage	3.0 4.5 5.5	1.5 2.25 2.75	0.9 1.35 1.65	0.9 1.35 1.65	V	$V_{OUT} = 0.1 V$ or $V_{CC} - 0.1 V$	
V _{OH}	Minimum High Level Output Voltage	3.0 4.5 5.5	2.99 4.49 5.49	2.9 4.4 5.4	2.9 4.4 5.4	V	I _{OUT} = -50 μA	
		3.0 4.5 5.5		2.56 3.86 4.86	2.46 3.76 4.76	v	*V _{IN} = V _{IL} or V _{IH} -12 mA I _{OH} -24 mA -24 mA	
V _{OL}	Maximum Low Level Output Voltage	3.0 4.5 5.5	0.002 0.001 0.001	0.1 0.1 0.1	0.1 0.1 0.1		I _{OUT} = 50 μΑ	
		3.0 4.5 5.5		0.36 0.36 0.36	0.44 0.44 0.44		*V _{IN} = V _{IL} or V _{IH} 12 mA I _{OL} 24 mA 24 mA	
I _{IN}	Maximum Input Leakage Current	5.5	C	±0.1	±1:0	μΑ	$V_{I} = V_{CC}, GND$	
I _{OLD}	†Minimum Dynamic	5.5	8	0	75	mA	V _{OLD} = 1.65 V Max	
I _{OHD}	Output Current	5.5			-75	mA	V _{OHD} = 3.85 V Min	
I _{CC}	Maximum Quiescent Supply Current	5.5	0	8.0	80	μΑ	$V_{IN} = V_{CC}$ or GND	

7

* All outputs loaded; thresholds on input associated with output under test. † Maximum test duration 2.0 ms, one output loaded at a time.

† Maximum test duration 2.0 ms, one output loaded at a time. Note: I_{IN} and I_{CC} @ 3.0 V are guaranteed to be less than or equal to the respective limit @ 5.5 V V_{CC}.

AC CHARACTERISTICS	(For Figures and Waveforms -	- See Section 3)
AC CHARACTERIOTICO	(i of i iguico and wavelonno	

			74AC			74AC			Fig. No.	
Symbol	Parameter	V _{CC} * (V)	T _A = +25°C C _L = 50 pF		T _A = -40°C to +85°C C _L = 50 pF		Unit			
			Min	Тур	Max	Min	Max			
t _{PLH}	Propagation Delay S_n to \overline{Z}_n		3.3 5.0	2.0 2.0	8.5 6.5	15.0 11.0	1.0 1.0	17.5 12.5	ns	3-6
t _{PHL}	Propagation Delay S_n to \overline{Z}_n		3.3 5.0	2.0 2.0	8.0 6.0	14.5 11.0	1.0 1.0	16.5 12.0	ns	3-6
t _{PLH}	Propagation Delay \overline{E}_n to \overline{Z}_n		3.3 5.0	2.0 2.0	6.0 4.5	13.5 9.5	1.0 1.0	16.0 11.0	ns	3-6
t _{PHL}	Propagation Delay \overline{E}_n to \overline{Z}_n		3.3 5.0	2.0 2.0	5.5 4.0	11.0 8.0	1.0 1.0	12.5 9.0	ns	3-6
t _{PLH}	Propagation Delay I_n to \overline{Z}_n		3.3 5.0	2.0 2.0	7.0 5.0	12.5 9.0	1.0 1.0	14.5 10.5	ns	3-5
t _{PHL}	Propagation Delay I_n to \overline{Z}_n		3.3 5.0	2.0 2.0	7.0 5.0	11.5 8.5	1.0 1.0	13.0 10.0	ns	3-5
	ge 3.3 V is 3.3 V ±0.3 V. ge 5.0 V is 5.0 V ±0.5 V.					4	01	4		
DC CHARA	ACTERISTICS			r	\bigcirc	6		\mathbf{O}		

DC CHARACTERISTICS

					Y C				
Symbol	Parameter	V _{CC} (V)	$74ACT$ $T_{A} = +25^{\circ}C$		T _A = +25°C		74ACT $T_A =$ -40°C to +85°C anteed Limits	Unit	Conditions
V _{IH}	Minimum High Level Input Voltage	4.5 5.5	тур 1.5 1.5	2.0 2.0	2.0 2.0 2.0	V	V _{OUT} = 0.1 V or V _{CC} – 0.1 V		
V _{IL}	Maximum Low Level Input Voltage	4.5 5.5	1.5 1.5	0.8 0.8	0.8 0.8	V	V_{OUT} = 0.1 V or V _{CC} – 0.1 V		
V _{OH}	Minimum High Level Output Voltage	4.5 5.5	4.49 5.49	4.4 5.4	4.4 5.4	V	l _{OUT} = -50 μA		
	C THE	4.5 5.5		3.86 4.86	3.76 4.76	V	$V_{IN} = V_{IL} \text{ or } V_{IH}$ -24 mA I_{OH} -24 mA		
V _{OL}	Maximum Low Level Output Voltage	4.5 5.5	0.001 0.001	0.1 0.1	0.1 0.1	V	l _{OUT} = 50 μA		
	Maximum Low Level Output Voltage Maximum Input	4.5 5.5		0.36 0.36	0.44 0.44	V	*V _{IN} = V _{IL} or V _{IH} 24 mA I _{OL} 24 mA		
I _{IN}	Maximum Input Leakage Current	5.5		±0.1	±1.0	μΑ	$V_{I} = V_{CC}, GND$		
ΔI_{CCT}	Additional Max. I _{CC} /Input	5.5	0.6		1.5	mA	$V_{I} = V_{CC} - 2.1 V$		
I _{OLD}	†Minimum Dynamic	5.5			75	mA	V _{OLD} = 1.65 V Max		
I _{OHD}	Output Current	5.5			-75	mA	V _{OHD} = 3.85 V Min		
Icc	Maximum Quiescent Supply Current	5.5		8.0	80	μΑ	V _{IN} = V _{CC} or GND		

* All outputs loaded; thresholds on input associated with output under test.

† Maximum test duration 2.0 ms, one output loaded at a time.


			74ACT			74ACT			
Symbol	Parameter	V _{CC} * (V)	T _A = +25°C C _L = 50 pF			T _A = -40°C to +85°C C _L = 50 pF		Unit	Fig. No.
			Min	Тур	Max	Min	Max		
t _{PLH}	Propagation Delay S_n to \overline{Z}_n	5.0	3.0	6.0	10.5	1.0	11.5	ns	3-6
t _{PHL}	Propagation Delay S_n to \overline{Z}_n	5.0	3.0	6.0	10.0	1.0	11.5	ns	3-6
t _{PLH}	Propagation Delay \overline{E}_n to \overline{Z}_n	5.0	2.0	4.5	8.0	1.0	8.5	ns	3-6
t _{PHL}	Propagation Delay \overline{E}_n to \overline{Z}_n	5.0	2.0	4.5	8.0	1.0	8.5	ns	3-6
t _{PLH}	Propagation Delay I_n to \overline{Z}_n	5.0	2.0	5.5	10.0	1.0	11.0	ns	3-5
t _{PHL}	Propagation Delay I_n to \overline{Z}_n	5.0	2.0	6.5	8.5	1.0	9.0	ns	3-5

AC CHARACTERISTICS (For Figures and Waveforms — See Section 3)

CAPACITANCE

	Parameter	Value Typ Unit	Test Conditions
IN	Input Capacitance	4,5 pF	V _{CC} = 5.0 V
PD	Power Dissipation Capacitance	50 pF	V _{CC} = 5.0 V
	Power Dissipation Capacitance		

OUTLINE DIMENSIONS



ON Semiconductor and images are registered trademarks of Semiconductor Components Industries, LLC (SCILLC). SCILLC reserves the right to make changes without further notice to any products herein. SCILLC makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does SCILLC assume any liability arising out of the application or use of any provided in SCILLC data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters which may be provided in SCILLC data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. SCILLC does not convey any license under its patent rights nor the rights of others. SCILLC products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other application in which the SCILLC product cate a situation where personal injury or death may occur. Should Buyer purchase or use SCILLC products for any such unintended or unauthorized application, Buyer shall indemnify and hold SCILLC and its officers, employees, subsidiaries, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use persons and sensing experts. SCILLC was negligent regarding the design or manufacture of the part. SCILLC is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor P.O. Box 5163, Denver, Colorado 80217 USA Phone: 303–675–2175 or 800–344–3860 Toll Free USA/Canada Fax: 303–675–2176 or 800–344–3867 Toll Free USA/Canada Email: orderlit@onsemi.com N. American Technical Support: 800–282–9855 Toll Free USA/Canada Europe, Middle East and Africa Technical Support:

Phone: 421 33 790 2910 Japan Customer Focus Center Phone: 81–3–5773–3850 ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative