# MOSFET – Power, P-Channel, Schottky Diode, ChipFET, FETKY, Schottky Barrier Diode

-20 V, -4.4 A, 4.1 A

#### **Features**

- Leadless SMD Package Featuring a MOSFET and Schottky Diode
- 40% Smaller than TSOP-6 Package
- Leadless SMD Package Provides Great Thermal Characteristics
- Independent Pinout to each Device to Ease Circuit Design
- Trench P-Channel for Low On Resistance
- Ultra Low V<sub>F</sub> Schottky
- Pb-Free Packages are Available

#### **Applications**

- Li-Ion Battery Charging
- High Side DC-DC Conversion Circuits
- High Side Drive for Small Brushless DC Motors
- Power Management in Portable, Battery Powered Products

#### MOSFET MAXIMUM RATINGS (T<sub>J</sub> = 25°C unless otherwise noted)

Param	Symbol	Value	Units		
Drain-to-Source Voltag	е		$V_{DSS}$	-20	V
Gate-to-Source Voltage	9		$V_{GS}$	±8.0	V
Continuous Drain	Steady	$T_J = 25^{\circ}C$	I <sub>D</sub>	-3.2	Α
Current (Note 1)	State	T <sub>J</sub> = 85°C		-2.3	
	t ≤ 5 s	T <sub>J</sub> = 25°C		-4.4	
Power Dissipation (Note 1)	Steady State	, ,		1.1	W
	t ≤ 5 s			2.1	
Pulsed Drain Current	t <sub>p</sub> =	10 μs	I <sub>DM</sub>	-13	Α
Operating Junction and	T <sub>J</sub> , T <sub>STG</sub>	–55 to 150	ç		
Source Current (Body D	I <sub>S</sub>	2.5	Α		
Lead Temperature for S (1/8" from case for 1		urposes	TL	260	°C

#### **SCHOTTKY DIODE MAXIMUM RATINGS**

 $(T_J = 25^{\circ}C \text{ unless otherwise noted})$ 

Parameter	Symbol	Value	Units
Peak Repetitive Reverse Voltage	$V_{RRM}$	20	V
DC Blocking Voltage	$V_{R}$	20	V

1




## ON Semiconductor®

http://onsemi.com

MOSFET						
V <sub>(BR)DSS</sub>	I <sub>D</sub> MAX					
00.17	64 mΩ @ -4.5 V	4.4.4				
–20 V	85 mΩ @ –2.5 V	–4.4 A				


#### **SCHOTTKY DIODE**

V <sub>R</sub> MAX	V <sub>F</sub> TYP	I <sub>F</sub> MAX
20 V	0.510 V	4.1 A





ChipFET CASE 1206A STYLE 3



D1 = Specific Device Code M = Month Code ■ = Pb-Free Package

#### **ORDERING INFORMATION**

See detailed ordering and shipping information in the package dimensions section on page 7 of this data sheet.

#### **SCHOTTKY DIODE MAXIMUM RATINGS**

(T<sub>J</sub> = 25°C unless otherwise noted)

Parai	Symbol	Value	Units		
Average Rectified Forward Current	Steady State	T <sub>J</sub> = 25°C	I <sub>F</sub>	2.2	>
	t ≤ 5 s			4.1	Α

Stresses exceeding Maximum Ratings may damage the device. Maximum Ratings are stress ratings only. Functional operation above the Recommended Operating Conditions is not implied. Extended exposure to stresses above the Recommended Operating Conditions may affect device reliability.

 Surface Mounted on FR4 Board using 1 in sq pad size (Cu area = 1.127 in sq [1 oz] including traces).

#### THERMAL RESISTANCE RATINGS

Parameter	Symbol	Max	Units
Junction-to-Ambient - Steady State (Note 2)	$R_{ heta JA}$	113	°C/W
Junction-to-Ambient - t ≤ 10 s (Note 2)	$R_{ hetaJA}$	60	°C/W

2. Surface Mounted on FR4 Board using 1 in sq pad size (Cu area = 1.127 in sq [1 oz] including traces).

#### MOSFET ELECTRICAL CHARACTERISTICS (T<sub>J</sub> = 25°C unless otherwise noted)

Parameter	Symbol	Test Condition	s	Min	Тур	Max	Units
OFF CHARACTERISTICS							
Drain-to-Source Breakdown Voltage	V <sub>(BR)DSS</sub>	$V_{GS} = 0 \text{ V}, I_D = -25$	50 μΑ	-20			V
Drain-to-Source Breakdown Voltage Temperature Coefficient	V <sub>(BR)DSS</sub> /T <sub>J</sub>				-15		mV/°C
Zero Gate Voltage Drain Current	I <sub>DSS</sub>	V 40VV 0V	T <sub>J</sub> = 25°C			-1.0	μΑ
		$V_{DS} = -16 \text{ V}, V_{GS} = 0 \text{ V}$	T <sub>J</sub> = 125°C			-5.0	
Gate-to-Source Leakage Current	I <sub>GSS</sub>	V <sub>DS</sub> = 0 V, V <sub>GS</sub> = ±	8.0 V			±100	nA
ON CHARACTERISTICS (Note 3)							
Gate Threshold Voltage	V <sub>GS(TH)</sub>	$V_{GS} = V_{DS}$ , $I_D = -2$	50 μΑ	-0.45		-1.5	V
Gate Threshold Temperature Coefficient	V <sub>GS(TH)</sub> /T <sub>J</sub>				2.7		mV/°C
Drain-to-Source On-Resistance	R <sub>DS(on)</sub>	$V_{GS} = -4.5, I_D = -3$	3.2 A		64	80	mΩ
		$V_{GS} = -2.5$ , $I_D = -2.2$ A $V_{GS} = -1.8$ , $I_D = -1.0$ A			85	110	1
					120	170	
Forward Transconductance	9 <sub>FS</sub>	$V_{DS} = -10 \text{ V}, I_D = -2.9 \text{ A}$			8.0		S
CHARGES AND CAPACITANCES							
Input Capacitance	C <sub>ISS</sub>				680		pF
Output Capacitance	Coss	$V_{GS} = 0 \text{ V, f} = 1.0 \text{ N}$ $V_{DS} = -10 \text{ V}$	ИHz,		100		
Reverse Transfer Capacitance	C <sub>RSS</sub>	103 - 10 t			70		
Total Gate Charge	Q <sub>G(TOT)</sub>				7.4		nC
Threshold Gate Charge	Q <sub>G(TH)</sub>	V <sub>GS</sub> = -4.5 V, V <sub>DS</sub> =	–10 V,		0.6		
Gate-to-Source Charge	$Q_{GS}$	$I_D = -3.2 \text{ A}$	·		1.4		
Gate-to-Drain Charge	$Q_{GD}$	1			2.5		
SWITCHING CHARACTERISTICS (No	ote 4)						
Turn-On Delay Time	t <sub>d(ON)</sub>	$V_{GS} = -4.5 \text{ V}, V_{DD} = -10 \text{ V},$ $I_{D} = -3.2 \text{ A}, R_{G} = 2.4 \Omega$			5.8		ns
Rise Time	t <sub>r</sub>				11.7		
Turn-Off Delay Time	t <sub>d(OFF)</sub>				16		
Fall Time	t <sub>f</sub>				12.4		
DRAIN-SOURCE DIODE CHARACTE	RISTICS						<u>-</u>
Forward Diode Voltage	$V_{SD}$	$V_{GS} = 0 \text{ V}, I_{S} = -2.5 \text{ A}$	T <sub>J</sub> = 25°C		-0.8	-1.2	V

# $\textbf{MOSFET ELECTRICAL CHARACTERISTICS} \ (T_J = 25^{\circ}\text{C unless otherwise noted})$

Parameter	Symbol	ymbol Test Conditions		Тур	Max	Units	
DRAIN-SOURCE DIODE CHARACTERISTICS							
Reverse Recovery Time	t <sub>RR</sub>			13.5		ns	
Charge Time	ta	V <sub>GS</sub> = 0 V, I <sub>S</sub> = -1.0 A ,		9.5			
Discharge Time	t <sub>b</sub>	$V_{GS} = 0 \text{ V, } I_{S} = -1.0 \text{ A},$ $dI_{S}/dt = 100 \text{ A}/\mu\text{s}$		4.0			
Reverse Recovery Charge	$Q_{RR}$			6.5		nC	


# SCHOTTKY DIODE ELECTRICAL CHARACTERISTICS ( $T_J = 25^{\circ}C$ unless otherwise noted)

Parameter	Symbol	Test Conditions	Min	Тур	Max	Units
Maximum Instantaneous	V <sub>F</sub>	I <sub>F</sub> = 0.1 A		0.425		V
Forward Voltage		I <sub>F</sub> = 1.0 A		0.510	0.575	
Maximum Instantaneous	I <sub>R</sub>	V <sub>R</sub> = 10 V			1.0	μΑ
Reverse Current		V <sub>R</sub> = 20 V			5.0	

Pulse Test: Pulse Width ≤ 300 μs, Duty Cycle ≤ 2%.
 Switching characteristics are independent of operating junction temperatures.

#### TYPICAL P-CHANNEL PERFORMANCE CURVES


 $(T_J = 25^{\circ}C \text{ unless otherwise noted})$ 



 $V_{DS} \ge -10 \text{ V}$ ID, DRAIN CURRENT (AMPS) 6 5 3  $T_C = -55^{\circ}C$ 2 25°C 100°C 2.5 0 0.5 1.5 2 3.5 -V<sub>GS</sub>, GATE-TO-SOURCE VOLTAGE (VOLTS)

Figure 1. On-Region Characteristics

Figure 2. Transfer Characteristics







Figure 3. On-Resistance vs. Gate-to-Source Voltage

Figure 4. On-Resistance vs. Drain Current and Gate Voltage







Figure 5. On–Resistance Variation with Temperature

Figure 6. Drain-to-Source Leakage Current vs. Voltage

#### **TYPICAL P-CHANNEL PERFORMANCE CURVES**

(T<sub>J</sub> = 25°C unless otherwise noted)



GATE-TO-SOURCE OR DRAIN-TO-SOURCE VOLTAGE (VOLTS)

Figure 7. Capacitance Variation




Figure 9. Resistive Switching Time Variation vs. Gate Resistance

# Figure 8. Gate-to-Source and Drain-to-Source Voltage vs. Total Charge





Figure 10. Diode Forward Voltage vs. Current

## TYPICAL SCHOTTKY PERFORMANCE CURVES (T<sub>J</sub> = 25°C unless otherwise noted)






Figure 11. Typical Forward Voltage

Figure 12. Maximum Forward Voltage





Figure 13. Typical Reverse Current

Figure 14. Maximum Reverse Current









Figure 16. Forward Power Dissipation

#### **DEVICE ORDERING INFORMATION**

Device	Package	Shipping <sup>†</sup>
NTHD3101FT1	ChipFET	3000 / Tape & Reel
NTHD3101FT1G	ChipFET (Pb-Free)	3000 / Tape & Reel
NTHD3101FT3	ChipFET	10000 / Tape & Reel
NTHD3101FT3G	ChipFET (Pb-Free)	10000 / Tape & Reel

<sup>†</sup>For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.





# **ChipFET™**

**DATE 19 MAY 2009** 


#### NOTES:

- DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982. CONTROLLING DIMENSION: MILLIMETER.
- MOLD GATE BURRS SHALL NOT EXCEED 0.13 MM PER SIDE. LEADFRAME TO MOLDED BODY OFFSET IN HORIZONTAL
- AND VERTICAL SHALL NOT EXCEED 0.08 MM.
  DIMENSIONS A AND B EXCLUSIVE OF MOLD GATE BURRS.
- NO MOLD FLASH ALLOWED ON THE TOP AND BOTTOM LEAD SURFACE.

	М	ILLIMETE	RS	INCHES			
DIM	MIN	NOM	MAX	MIN	NOM	MAX	
Α	1.00	1.05	1.10	0.039	0.041	0.043	
b	0.25	0.30	0.35	0.010	0.012	0.014	
С	0.10	0.15	0.20	0.004	0.006	0.008	
D	2.95	3.05	3.10	0.116	0.120	0.122	
E	1.55	1.65	1.70	0.061	0.065	0.067	
е		0.65 BSC		0.025 BSC			
e1		0.55 BSC		0.022 BSC			
L	0.28	0.35	0.42	0.011	0.014	0.017	
HE	1.80	1.90	2.00	0.071	0.075	0.079	
θ	5° NOM				5° NOM		

STYLE 1:	STYLE 2:	STYLE 3:	STYLE 4:	STYLE 5:	STYLE 6:
PIN 1. DRAIN	PIN 1. SOURCE 1	PIN 1. ANODE	PIN 1. COLLECTOR	PIN 1. ANODE	PIN 1. ANODE
<ol><li>DRAIN</li></ol>	2. GATE 1	2. ANODE	2. COLLECTOR	<ol><li>ANODE</li></ol>	2. DRAIN
<ol><li>DRAIN</li></ol>	<ol><li>SOURCE 2</li></ol>	<ol><li>SOURCE</li></ol>	<ol><li>COLLECTOR</li></ol>	<ol><li>DRAIN</li></ol>	3. DRAIN
<ol><li>GATE</li></ol>	4. GATE 2	4. GATE	4. BASE	<ol><li>DRAIN</li></ol>	4. GATE
<ol><li>SOURCE</li></ol>	5. DRAIN 2	5. DRAIN	<ol><li>EMITTER</li></ol>	<ol><li>SOURCE</li></ol>	5. SOURCE
<ol><li>DRAIN</li></ol>	6. DRAIN 2	6. DRAIN	<ol><li>COLLECTOR</li></ol>	<ol><li>GATE</li></ol>	6. DRAIN
<ol><li>DRAIN</li></ol>	7. DRAIN 1	<ol><li>CATHODE</li></ol>	<ol><li>COLLECTOR</li></ol>	<ol><li>CATHODE</li></ol>	7. DRAIN
8. DRAIN	8. DRAIN 1	<ol><li>CATHODE</li></ol>	<ol><li>COLLECTOR</li></ol>	<ol><li>CATHODE</li></ol>	8. CATHODE / DRAIN

#### **SOLDERING FOOTPRINT**



#### **GENERIC MARKING DIAGRAM\***



XXX = Specific Device Code

М = Month Code = Pb-Free Package

(Note: Microdot may be in either location)

\*This information is generic. Please refer to device data sheet for actual part marking. Pb-Free indicator, "G" or microdot "•", may or may not be present. Some products may not follow the Generic Marking.


## **OPTIONAL SOLDERING FOOTPRINTS ON PAGE 2**

DOCUMENT NUMBER:	98AON03078D	Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red.	
DESCRIPTION:	ChipFET		PAGE 1 OF 2

onsemi and ONSEMI are trademarks of Semiconductor Components Industries, LLC dba onsemi or its subsidiaries in the United States and/or other countries. onsemi reserves brisefin and of 160 m are trademarked so defined values of services and of the confined values and of the values of the confined values and of the values of the confined values and of the values of the special, consequential or incidental damages. onsemi does not convey any license under its patent rights nor the rights of others.

**DATE 19 MAY 2009** 

#### **ADDITIONAL SOLDERING FOOTPRINTS\***



\*For additional information on our Pb-Free strategy and soldering details, please download the **onsemi** Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

DOCUMENT NUMBER:	98AON03078D	Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red.	
DESCRIPTION:	ChipFET		PAGE 2 OF 2

onsemi and ONSEMi are trademarks of Semiconductor Components Industries, LLC dba onsemi or its subsidiaries in the United States and/or other countries. onsemi reserves the right to make changes without further notice to any products herein. onsemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. onsemi does not convey any license under its patent rights nor the rights of others.

onsemi, ONSEMI., and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries. onsemi owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of onsemi's product/patent coverage may be accessed at <a href="www.onsemi.com/site/pdf/Patent-Marking.pdf">www.onsemi.com/site/pdf/Patent-Marking.pdf</a>. onsemi reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and onsemi makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using **onsemi** products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by **onsemi**. "Typical" parameters which may be provided in **onsemi** data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. **onsemi** does not convey any license under any of its intellectual property rights nor the rights of others. **onsemi** products are not designed, intended, or authorized for use as a critical component in life support systems. or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use **onsemi** products for any such unintended or unauthorized application, Buyer shall indemnify and hold **onsemi** and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that **onsemi** was negligent regarding the design or manufacture of the part. **onsemi** is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

#### ADDITIONAL INFORMATION

TECHNICAL PUBLICATIONS:

 $\textbf{Technical Library:} \ \underline{www.onsemi.com/design/resources/technical-documentation}$ 

onsemi Website: www.onsemi.com

ONLINE SUPPORT: www.onsemi.com/support

For additional information, please contact your local Sales Representative at

www.onsemi.com/support/sales