Power MOSFET

25 V, 193 A, Single N-Channel, SO-8FL

Features

- Optimized Design to Minimize Conduction and Switching Losses
- Optimized Package to Minimize Parasitic Inductances
- Optimized material for improved thermal performance
- These Devices are Pb–Free, Halogen Free/BFR Free and are RoHS Compliant

Applications

- High Performance DC-DC Converters
- System Voltage Rails
- Netcom, Telecom
- Servers & Point of Load

MAXIMUM RATINGS ($T_J = 25^{\circ}C$ unless otherwise stated)

Parameter	Symbol	Value	Units
Drain-to-Source Voltage	V_{DSS}	25	>
Gate-to-Source Voltage	V_{GS}	±20	V
Continuous Drain Current $R_{\theta JA}$ ($T_A = 25^{\circ}C$, Note 1)	I _D	37	Α
Power Dissipation $R_{\theta JA}$ ($T_A = 25^{\circ}C$, Note 1)	P _D	3.13	W
Continuous Drain Current $R_{\theta JC}$ ($T_C = 25^{\circ}C$, Note 1)	I _D	193	Α
Power Dissipation $R_{\theta JC}$ ($T_C = 25^{\circ}C$, Note 1)	P _D	83	W
Pulsed Drain Current (t _p = 10 μs)	I _{DM}	412	Α
Single Pulse Drain-to-Source Avalanche Energy (Note 1) ($I_L = 47 \text{ A}_{pk}$, $L = 0.3 \text{ mH}$)	E _{AS}	331	mJ
Drain to Source dV/dt	dV/dt	7	V/ns
Maximum Junction Temperature	$T_{J(max)}$	150	°C
Storage Temperature Range	T _{STG}	–55 to 150	°C
Lead Temperature Soldering Reflow (SMD Styles Only), Pb-Free Versions (Note 2)	T _{SLD}	260	°C

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

- Values based on copper area of 645 mm² (or 1 in²) of 2 oz copper thickness and FR4 PCB substrate.
- For more information, please refer to our Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.
- This is the absolute maximum rating. Parts are 100% UIS tested at T_J = 25°C, V_{GS} = 10 V, I_I = 31 A, E_{AS} = 144 mJ.

THERMALCHARACTERISTICS

Parameter	Symbol	Max	Units
Thermal Resistance, Junction-to-Ambient (Note 1 and 4) Junction-to-Case (Note 1 and 4)	$egin{array}{c} {\sf R}_{ heta {\sf JA}} \ {\sf R}_{ heta {\sf JC}} \end{array}$	40.0 1.5	°C/W

4. Thermal Resistance $R_{\theta JA}$ and $R_{\theta JC}$ as defined in JESD51–3.




ON Semiconductor®

http://onsemi.com


V _{GS}	MAX R _{DS(on)}	TYP Q _{GTOT}
4.5 V	$2.2~\text{m}\Omega$	18 nC
10 V	1.4 m Ω	38.5 nC

PIN CONNECTIONS

SO8-FL (5 x 6 mm)



N-CHANNEL MOSFET



ORDERING INFORMATION

See detailed ordering and shipping information on page 7 of this data sheet.

ELECTRICAL CHARACTERISTICS (T_J = 25°C unless otherwise specified)

Parameter	Symbol	Test Condi	tion	Min	Тур	Max	Unit	
OFF CHARACTERISTICS	•				•		•	
Drain-to-Source Breakdown Voltage	V _{(BR)DSS}	$V_{GS} = 0 \text{ V}, I_D =$	250 μΑ	25			V	
Drain-to-Source Breakdown Voltage Temperature Coefficient	V _{(BR)DSS} /				18.5		mV/°C	
Zero Gate Voltage Drain Current	I _{DSS}	$V_{GS} = 0 V$	T _J = 25°C			1	μΑ	
		V _{DS} = 20 V	T _J = 125°C			20		
Gate-to-Source Leakage Current	I _{GSS}	$V_{DS} = 0 \text{ V}, V_{GS}$	s = 20 V			100	nA	
ON CHARACTERISTICS (Note 5)								
Gate Threshold Voltage	V _{GS(TH)}	$V_{GS} = V_{DS}, I_D =$	= 250 μΑ	1.2		2.1	V	
Negative Threshold Temperature Coefficient	V _{GS(TH)} /T _J				3.7		mV/°C	
Drain-to-Source On Resistance	R _{DS(on)}	V _{GS} = 10 V	I _D = 30 A		1.1	1.4	mΩ	
		V _{GS} = 4.5 V	I _D = 30 A		1.7	2.2	11152	
Forward Transconductance	9FS	$V_{DS} = 12 \text{ V}, I_{D}$	= 15 A		84		S	
CHARGES, CAPACITANCES & GATE RESIS	STANCE							
Input Capacitance	C _{ISS}	V _{GS} = 0 V, f = 1 MHz, V _{DS} = 12 V			2651			
Output Capacitance	Coss				1814		pF	
Reverse Transfer Capacitance	C _{RSS}				103			
Total Gate Charge	$Q_{G(TOT)}$	$V_{GS} = 4.5 \text{ V}, V_{DS} = 12 \text{ V}; I_D = 30 \text{ A}$ $V_{GS} = 10 \text{ V}, V_{DS} = 12 \text{ V}; I_D = 30 \text{ A}$			18		nC	
Threshold Gate Charge	Q _{G(TH)}				2.7			
Gate-to-Source Charge	Q_{GS}				7.2			
Gate-to-Drain Charge	Q_{GD}				4.2			
Total Gate Charge	$Q_{G(TOT)}$				38.5		nC	
Gate Resistance	R_{G}	T _A = 25°C			1.0	2	Ω	
SWITCHING CHARACTERISTICS, $V_{GS} = 4.5$	V (Note 5)							
Turn-On Delay Time	t _{d(ON)}				13.1			
Rise Time	t _r	$V_{GS} = 4.5 \text{ V}, V_{DD} = 12$	2 V, I _D = 15 A,		20		ns	
Turn-Off Delay Time	t _{d(OFF)}	$R_{G} = 3.0$	Ω		22.2			
Fall Time	t _f				9.1			
SWITCHING CHARACTERISTICS, $V_{GS} = 10$	V (Note 5)							
Turn-On Delay Time	t _{d(ON)}				9.5			
Rise Time	t _r	V _{GS} = 10 V, V _{DI}	₀ = 12 V,		18.5		1	
Turn-Off Delay Time	t _{d(OFF)}	$I_D = 15 \text{ A}, R_G = 3.0 \Omega$			30.3		ns	
Fall Time	t _f				5			
DRAIN-SOURCE DIODE CHARACTERISTIC	s							
Forward Diode Voltage	V_{SD}	V _{GS} = 0 V,	$T_J = 25^{\circ}C$		0.75	1.1		
		I _S = 10 A	T _J = 125°C		0.56		V	
Reverse Recovery Time	t _{RR}	$V_{GS} = 0 \text{ V, dIS/dt} = 100 \text{ A/}\mu\text{s,}$ $I_{S} = 30 \text{ A}$			46.3			
Charge Time	ta				23.9		ns	
Discharge Time	t _b				22.4			
Reverse Recovery Charge	Q_{RR}				51		nC	

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.

5. Pulse Test: pulse width ≤ 300 μs, duty cycle ≤ 2%.

6. Switching characteristics are independent of operating junction temperatures.

ELECTRICAL CHARACTERISTICS (T_J = 25°C unless otherwise specified)

		' '				
Parameter	Symbol	Test Condition	Min	Тур	Max	Unit
PACKAGE PARASITIC VALUES						
Source Inductance	L _S			0.57		nΗ
Drain Inductance	L _D	T _A = 25°C		0.13		nΗ
Gate Inductance	L _G			1.37		nΗ

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.

5. Pulse Test: pulse width $\leq 300~\mu s$, duty cycle $\leq 2\%$.

6. Switching characteristics are independent of operating junction temperatures.

TYPICAL CHARACTERISTICS




Figure 1. On-Region Characteristics

Figure 2. Transfer Characteristics

2.5

-55°C

3.5

3.0




Figure 3. On-Resistance vs. V_{GS}

Figure 4. On-Resistance vs. Drain Current and **Gate Voltage**




Figure 5. On-Resistance Variation with **Temperature**

Figure 6. Drain-to-Source Leakage Current vs. Voltage

TYPICAL CHARACTERISTICS




Figure 7. Capacitance Variation




Figure 8. Gate-to-Source and Drain-to-Source Voltage vs. Total Charge




Figure 9. Resistive Switching Time Variation vs. Gate Resistance




Figure 10. Diode Forward Voltage vs. Current




Figure 11. Maximum Rated Forward Biased Safe Operating Area




Figure 12. Maximum Avalanche Energy vs. Starting Junction Temperature

TYPICAL CHARACTERISTICS




Figure 13. Thermal Characteristics





Figure 14. GFS vs. I_D

Figure 15. Avalanche Characteristics

ORDERING INFORMATION

Device	Package	Shipping [†]
NTMFS4H02NT1G	SO8-FL (Pb-Free)	1500 / Tape & Reel
NTMFS4H02NT3G	SO8-FL (Pb-Free)	5000 / Tape & Reel

[†]For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.



A = Assembly Location

Y = Year

W = Work Week
ZZ = Lot Traceability





0.10

SIDE VIEW

DFN5 5x6, 1.27P (SO-8FL) CASE 488AA **ISSUE N**

DATE 25 JUN 2018

NOTES:

- DIMENSIONING AND TOLERANCING PER
- ASME Y14.5M, 1994.
 2. CONTROLLING DIMENSION: MILLIMETER.
 3. DIMENSION D1 AND E1 DO NOT INCLUDE
- MOLD FLASH PROTRUSIONS OR GATE BURRS

	MILLIMETERS			
DIM	MIN	NOM	MAX	
Α	0.90	1.00	1.10	
A1	0.00		0.05	
b	0.33	0.41	0.51	
С	0.23	0.28	0.33	
D	5.00	5.15	5.30	
D1	4.70	4.90	5.10	
D2	3.80	4.00	4.20	
E	6.00	6.15	6.30	
E1	5.70	5.90	6.10	
E2	3.45	3.65	3.85	
е		1.27 BSC)	
G	0.51	0.575	0.71	
K	1.20	1.35	1.50	
L	0.51	0.575	0.71	
L1	0.125 REF			
М	3.00	3.40 3.8		
θ	0 °		12 °	

GENERIC MARKING DIAGRAM*





XXXXXX = Specific Device Code

= Assembly Location Α

Υ = Year W = Work Week ZZ = Lot Traceability

*This information is generic. Please refer to device data sheet for actual part marking. Pb-Free indicator, "G" or microdot " ■", may or may not be present. Some products may not follow the Generic Marking.





DETAIL A

*For additional information on our Pb-Free strategy and soldering details, please download the onsemi Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

	DOCUMENT NUMBER:	98AON14036D	Electronic versions are uncontrolled except when accessed directly from the Document Repositor Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red.	
ſ	DESCRIPTION:	DFN5 5x6, 1.27P (SO-8FL)		PAGE 1 OF 1

onsemi and ONSEMI. are trademarks of Semiconductor Components Industries, LLC dba onsemi or its subsidiaries in the United States and/or other countries. onsemi reserves the right to make changes without further notice to any products herein. **onsemi** makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. onsemi does not convey any license under its patent rights nor the rights of others.

onsemi, ONSEMI., and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries. onsemi owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of onsemi's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. onsemi reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and onsemi makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using **onsemi** products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by **onsemi**. "Typical" parameters which may be provided in **onsemi** data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. **onsemi** does not convey any license under any of its intellectual property rights nor the rights of others. **onsemi** products are not designed, intended, or authorized for use as a critical component in life support systems. or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use **onsemi** products for any such unintended or unauthorized application, Buyer shall indemnify and hold **onsemi** and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that **onsemi** was negligent regarding the design or manufacture of the part. **onsemi** is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

ADDITIONAL INFORMATION

TECHNICAL PUBLICATIONS:

 $\textbf{Technical Library:} \ \underline{www.onsemi.com/design/resources/technical-documentation}$

onsemi Website: www.onsemi.com

ONLINE SUPPORT: www.onsemi.com/support

For additional information, please contact your local Sales Representative at

www.onsemi.com/support/sales