IGBT

This Insulated Gate Bipolar Transistor (IGBT) features a robust and cost effective Trench construction, and provides superior performance in demanding switching applications, offering both low on state voltage and minimal switching loss.

Features

- Low Saturation Voltage using Trench with Field Stop Technology
- Low Switching Loss Reduces System Power Dissipation
- Optimized for High Speed Switching
- 5 µs Short-Circuit Capability
- These are Pb-Free Devices

Typical Applications

- Power Factor Correction
- Solar Inverters
- Uninterruptable Power Supply (UPS)

ABSOLUTE MAXIMUM RATINGS

Rating	Symbol	Value	Unit
Collector-emitter voltage	V_{CES}	600	V
Collector current @ Tc = 25°C @ Tc = 100°C	I _C	100 50	A
Pulsed collector current, T _{pulse} limited by T _{Jmax}	I _{CM}	200	Α
Short–circuit withstand time $V_{GE} = 15 \text{ V}, V_{CE} = 400 \text{ V},$ $T_{J} \le +150 ^{\circ}\text{C}$	t _{SC}	5	μS
Gate-emitter voltage	V_{GE}	±20	V
Power Dissipation @ Tc = 25°C @ Tc = 100°C	P _D	223 89	W
Operating junction temperature range	TJ	–55 to +150	°C
Storage temperature range	T _{stg}	-55 to +150	°C
Lead temperature for soldering, 1/8" from case for 5 seconds	T _{SLD}	260	°C


Stresses exceeding Maximum Ratings may damage the device. Maximum Ratings are stress ratings only. Functional operation above the Recommended Operating Conditions is not implied. Extended exposure to stresses above the Recommended Operating Conditions may affect device reliability.




ON Semiconductor®

http://onsemi.com

50 A, 600 V V_{CEsat} = 1.65 V





MARKING DIAGRAM



A = Assembly Location

Y = Year WW = Work Week G = Pb-Free Package

ORDERING INFORMATION

Device	Package	Shipping
NGTG50N60FLWG	TO-247 (Pb-Free)	30 Units / Rail


THERMAL CHARACTERISTICS


Rating	Symbol	Value	Unit
Thermal resistance junction-to-case, for IGBT	$R_{ heta JC}$	0.56	°C/W
Thermal resistance junction-to-ambient	$R_{ hetaJA}$	40	°C/W


ELECTRICAL CHARACTERISTICS (T_J = 25°C unless otherwise specified)

Parameter	Test Conditions	Symbol	Min	Тур	Max	Unit
STATIC CHARACTERISTIC	•					•
Collector-emitter breakdown voltage, gate-emitter short-circuited	$V_{GE} = 0 \text{ V, I}_{C} = 500 \mu\text{A}$	V _{(BR)CES}	600	_	-	V
Collector-emitter saturation voltage	V _{GE} = 15 V, I _C = 50 A V _{GE} = 15 V, I _C = 25 A, T _J = 150°C	V _{CEsat}	1.40	1.65 1.85	1.90	V
Gate-emitter threshold voltage	$V_{GE} = V_{CE}, I_{C} = 350 \mu A$	V _{GE(th)}	4.5	5.5	6.5	V
Collector-emitter cut-off current, gate- emitter short-circuited	V _{GE} = 0 V, V _{CE} = 600 V V _{GE} = 0 V, V _{CE} = 600 V, T _J = 150°C	I _{CES}	- -	_ _	0.5 2	mA
Gate leakage current, collector-emitter short-circuited	V _{GE} = 20 V , V _{CE} = 0 V	I _{GES}	-	_	200	nA
DYNAMIC CHARACTERISTIC	•	•		•		•
Input capacitance		C _{ies}	-	7302	-	pF
Output capacitance	V _{CE} = 20 V, V _{GE} = 0 V, f = 1 MHz	C _{oes}	-	220	-	
Reverse transfer capacitance	7	C _{res}	-	190	-	
Gate charge total		Q_g	-	310	-	nC
Gate to emitter charge	V _{CE} = 480 V, I _C = 50 A, V _{GE} = 15 V	Q _{ge}	-	60	-	
Gate to collector charge	7	Q _{gc}	-	150	-	
SWITCHING CHARACTERISTIC, INDUC	TIVE LOAD					
Turn-on delay time		t _{d(on)}	-	116	-	ns
Rise time	1	t _r	-	43	-	
Turn-off delay time	T _J = 25°C	t _{d(off)}	-	292	-	
Fall time	$V_{CC} = 400 \text{ V, } I_{C} = 50 \text{ A}$ $R_{c} = 10 \Omega$	t _f	-	78	-	
Turn-on switching loss	$R_g = 10 \Omega$ $V_{GE} = 0 \text{ V/ } 15 \text{ V*}$	E _{on}	-	1.1	-	mJ
Turn-off switching loss]	E _{off}	-	0.6	-	
Total switching loss	1	E _{ts}	-	1.7	-	
Turn-on delay time		t _{d(on)}	-	110	-	ns
Rise time		t _r	-	45	-	
Turn-off delay time	T _J = 150°C	t _{d(off)}	-	300	-	
Fall time	$V_{CC} = 400 \text{ V}, I_{C} = 50 \text{ A}$ $R_{c} = 10 \Omega$	t _f	-	105	-	
Turn-on switching loss	$R_g = 10 \Omega$ $V_{GE} = 0 \text{ V/ } 15 \text{ V*}$	E _{on}	-	1.4	_	mJ
Turn-off switching loss		E _{off}	-	1.1	-	
Total switching loss		E _{ts}	-	2.5	_]

^{*}Includes diode reverse recovery loss using NGTB50N60FLWG.













Figure 4. Typical Transfer Characteristics






Figure 6. Typical Capacitance




Figure 7. Typical Gate Charge




Figure 8. Switching Loss vs. Temperature




Figure 9. Switching Time vs. Temperature




Figure 10. Switching Loss vs. I_C




Figure 11. Switching Time vs. I_C




Figure 12. Switching Loss vs. R_G




Figure 13. Switching Time vs. R_G




Figure 14. Switching Loss vs. V_{CE}





Figure 15. Switching Time vs. V_{CE}






Figure 17. Reverse Bias Safe Operating Area




Figure 18. IGBT Transient Thermal Impedance




Figure 19. Test Circuit for Switching Characteristics




Figure 20. Definition of Turn On Waveform





Figure 21. Definition of Turn Off Waveform





3X D

♦0.25 (0.010)**₩** Y AS

TO-247 CASE 340L ISSUE G


DATE 06 OCT 2021

NOTES

- 1. DIMENSIONING AND TOLERANCING PER ASME Y14.5M, 1982.
- 2. CONTROLLING DIMENSION: MILLIMETER

	MILLIMETERS		INC	HES	
DIM	MIN.	MAX.	MIN.	MAX.	
Α	20.32	21.08	0.800	0.830	
В	15.75	16.26	0.620	0.640	
С	4.70	5.30	0.185	0.209	
D	1.00	1.40	0.040	0.055	
Ε	1.90	2.60	0.075	0.102	
F	1.65	2.13	0.065	0.084	
G	5.45	5.45 BSC		0.215 BSC	
Н	1.50	2.49	0.059	0.098	
J	0.40	0.80	0.016	0.031	
К	19.81	20.83	0.780	0.820	
L	5.40	6.20	0.212	0.244	
N	4.32	5.49	0.170	0.216	
Р		4.50		0.177	
Q	3.55	3.65	0.140	0.144	
U	6.15	BSC	0.242	BSC	
W	2.87	3.12	0.113	0.123	

GENERIC MARKING DIAGRAM*



STYLE 1: PIN 1. GATE 2. DRAIN 3. SOURCE 4. DRAIN

> PIN 1. CATHODE 2. ANODE

3. GATE 4. ANODE

STYLE 5:

STYLE 2:
PIN 1. ANODE
2. CATHODE (S)
3. ANODE 2
4. CATHODES (S)

PIN 1. MAIN TERMINAL 1 2. MAIN TERMINAL 2

3. GATE 4. MAIN TERMINAL 2

STYLE 6:

STYLE 3:
PIN 1. BASE
2. COLLECTOR
3. EMITTER
4. COLLECTOR

STYLE 4:
PIN 1. GATE
2. COLLECTOR
3. EMITTER
4. COLLECTOR

XXXXX = Specific Device Code A = Assembly Location

Y = Year
WW = Work Week
G = Pb-Free Package

*This information is generic. Please refer to device data sheet for actual part marking. Pb-Free indicator, "G" or microdot "•", may or may not be present. Some products may not follow the Generic Marking.

I	DOCUMENT NUMBER:	98ASB15080C
ı		

Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red.

DESCRIPTION: TO-247

PAGE 1 OF 1

onsemi and ONSeMi are trademarks of Semiconductor Components Industries, LLC dba onsemi or its subsidiaries in the United States and/or other countries. onsemi reserves the right to make changes without further notice to any products herein. onsemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. onsemi does not convey any license under its patent rights nor the rights of others.

onsemi, ONSEMI., and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries. onsemi owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of onsemi's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. onsemi reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and onsemi makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using **onsemi** products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by **onsemi**. "Typical" parameters which may be provided in **onsemi** data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. **onsemi** does not convey any license under any of its intellectual property rights nor the rights of others. **onsemi** products are not designed, intended, or authorized for use as a critical component in life support systems. or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use **onsemi** products for any such unintended or unauthorized application, Buyer shall indemnify and hold **onsemi** and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that **onsemi** was negligent regarding the design or manufacture of the part. **onsemi** is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

ADDITIONAL INFORMATION

TECHNICAL PUBLICATIONS:

 $\textbf{Technical Library:} \ \underline{www.onsemi.com/design/resources/technical-documentation}$

onsemi Website: www.onsemi.com

ONLINE SUPPORT: www.onsemi.com/support

For additional information, please contact your local Sales Representative at

www.onsemi.com/support/sales