# MMSD4148, SMMSD4148

## **Switching Diode**

#### **Features**

- SOD-123 Surface Mount Package
- High Breakdown Voltage
- Fast Speed Switching Time
- S Prefix for Automotive and Other Applications Requiring Unique Site and Control Change Requirements; AEC-Q101 Qualified and PPAP Capable\*
- These Devices are Pb–Free, Halogen Free/BFR Free and are RoHS Compliant

## **MAXIMUM RATINGS**

Rating	Symbol	Value	Unit
Continuous Reverse Voltage	V <sub>R</sub>	100	V
Forward Current	l <sub>F</sub>	200	mA
	I <sub>FSM</sub>	1.0 2.0	Α
Repetitive Peak Forward Current (Pulse Wave = 1 sec, Duty Cycle = 66%)	I <sub>FRM</sub>	0.5	А
Operating and Storage Junction Temperature Range	T <sub>J</sub> , T <sub>stg</sub>	-55 to +150	°C

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

1. Typical Values

## THERMAL CHARACTERISTICS

Characteristic	Symbol	Max	Unit
Total Device Dissipation FR–5 Board (Note 2) $T_{A} = 25^{\circ}C$	$P_{D}$	425	mW
Derate above 25°C		3.4	mW/°C
Thermal Resistance Junction-to-Ambient	$R_{\theta JA}$	290	°C/W

2.  $FR-5 = 1.0 \text{ oz Cu}, 1.0 \text{ in}^2 \text{ pad}$ 



## ON Semiconductor®

www.onsemi.com



SOD-123 CASE 425 STYLE 1



#### **MARKING DIAGRAM**



5I = Device Code

M = Date Code

= Pb-Free Package

(Note: Microdot may be in either location)

## **ORDERING INFORMATION**

Device	Package	Shipping <sup>†</sup>
MMSD4148T1G	SOD-123 (Pb-Free)	3,000 / Tape & Reel
SMMSD4148T1G*	SOD-123 (Pb-Free)	3,000 / Tape & Reel
MMSD4148T3G	SOD-123 (Pb-Free)	10,000 / Tape & Reel
SMMSD4148T3G*	SOD-123 (Pb-Free)	10,000 / Tape & Reel


†For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.

## MMSD4148, SMMSD4148

## **ELECTRICAL CHARACTERISTICS** (T<sub>A</sub> = 25°C unless otherwise noted)

Characteristic	Symbol	Min	Max	Unit
OFF CHARACTERISTICS	•			
Reverse Breakdown Voltage (I <sub>BR</sub> = 100 μA)	V <sub>(BR)</sub>	100	_	V
Reverse Voltage Leakage Current $(V_R = 20 \text{ V})$ $(V_R = 75 \text{ V})$	I <sub>R</sub>	- -	25 5.0	nA μA
Forward Voltage (I <sub>F</sub> = 10 mA)	V <sub>F</sub>	_	1000	mV
Diode Capacitance (V <sub>R</sub> = 0 V, f = 1.0 MHz)	C <sub>D</sub>	-	4.0	pF
Reverse Recovery Time (I <sub>F</sub> = I <sub>R</sub> = 10 mA) (Figure 1)	t <sub>rr</sub>	_	4.0	ns

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.



- 1. A 2.0  $k\Omega$  variable resistor adjusted for a Forward Current (IF) of 10 mA.
- 2. Input pulse is adjusted so  $I_{R(peak)}$  is equal to 10 mA.
- 3.  $t_p \gg t_{rr}$

Figure 1. Recovery Time Equivalent Test Circuit

## MMSD4148, SMMSD4148




Figure 2. Forward Voltage




Figure 3. Leakage Current





Figure 4. Capacitance







## SOD-123 2-LEAD, 1.60x2.69x1.16 CASE 425 ISSUE H


**DATE 29 FEB 2024** 



TOP VIEW








#### NOTES:

- . DIMENSION AND TOLERANCING PER ASME Y14.5M, 2018
- 2. CONTROLLING DIMENSION: MILLIMETERS

	MILLIMETER			
DIM	MIN.	N□M.	MAX.	
А	0.94	1.17	1.35	
A1	0.00	0.05	0.10	
A2	1.16 REF.			
b	0.51	0.61	0.71	
C	_	_	0.15	
D	1.40	1.60	1.80	
E	2.54	2.69	2.84	
Н	3.56	3.68	3,86	
L	0.25 REF.			
S	0°		10°	
θ1	0°		10°	



RECOMMENDED MOUNTING FOOTPRINT \*For additional information on or Pb-Free strategy and soldering details, please download the DN Semiconductor Soldering and Mounting Techniques Reference manual SDLDERRM/D.

# GENERIC MARKING DIAGRAM\*



XXX = Specific Device Code

M = Date Code

= Pb-Free Package

(Note: Microdot may be in either location)

\*This information is generic. Please refer to device data sheet for actual part marking. Pb-Free indicator, "G" or microdot "•", may or may not be present. Some products may not follow the Generic Marking.

STYLE 1: PIN 1. CATHODE

DOCUMENT NUMBER:	98ASB42927B	Electronic versions are uncontrolled except when accessed directly from the Document Repository Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red.		
DESCRIPTION:	SOD-123 2-LEAD, 1.60x2.69x1.16		PAGE 1 OF 1	

onsemi and ONSEMI are trademarks of Semiconductor Components Industries, LLC dba onsemi or its subsidiaries in the United States and/or other countries. onsemi reserves the right to make changes without further notice to any products herein. onsemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. onsemi does not convey any license under its patent rights nor the rights of others.

onsemi, Onsemi, and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries. onsemi owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of onsemi's product/patent coverage may be accessed at <a href="www.onsemi.com/site/pdf/Patent-Marking.pdf">www.onsemi.com/site/pdf/Patent-Marking.pdf</a>. Onsemi reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and onsemi makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using onsemi products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by onsemi. "Typical" parameters which may be provided in onsemi data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. onsemi does not convey any license under any of its intellectual property rights nor the rights of others. onsemi products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA class 3 medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase

#### ADDITIONAL INFORMATION

**TECHNICAL PUBLICATIONS:** 

 $\textbf{Technical Library:} \ \underline{www.onsemi.com/design/resources/technical-documentation}$ 

onsemi Website: www.onsemi.com

ONLINE SUPPORT: www.onsemi.com/support

For additional information, please contact your local Sales Representative at

www.onsemi.com/support/sales